



STATE OF UTAH - DEPARTMENT OF ADMINISTRATIVE SERVICES

**Division of Facilities Construction and Management**

**DFCM**

**STANDARD LOW BID PROJECT  
Project Budgets Over \$100,000**

**October 29, 2008**

**RANDALL JONES THEATER LIGHTING  
AND DIMMING SYSTEM**

**SOUTHERN UTAH UNIVERSITY**

**CEDAR CITY, UTAH**

DFCM Project Number: 08108730

**Spectrum Engineering  
801-401-8465  
175 South Main Street Suite 300,  
Salt Lake City, Utah**

# TABLE OF CONTENTS

|  | <u>Page Numbers</u> |
|--|---------------------|
| Title Sheet                                | 1                   |
| Table of Contents                          | 2                   |
| Notice to Contractors                      | 3                   |
| Project Description                        | 4                   |
| Project Schedule                           | 5                   |
| Bid Form                                   | 6                   |
| Instructions to Bidders                    | 8                   |
| Bid Bond                                   | 12                  |
| Instructions and Subcontractors List Form  | 13                  |
| Contractor's Agreement                     | 16                  |
| Performance Bond                           | 21                  |
| Payment Bond                               | 22                  |
| Certificate of Substantial Completion      | 23                  |
| General Contractor Past Performance Rating |                     |

Current copies of the following documents are hereby made part of these contract documents by reference. These documents are available on the DFCM web site at <http://dfcm.utah.gov> or are available upon request from DFCM.

DFCM Supplemental General Conditions dated July 15, 2008  
DFCM General Conditions dated May 25, 2005.  
DFCM Application and Certification for Payment dated May 25, 2005.

Technical Specifications : Attached and dated August 28, 2008  
Drawings: Attached and dated August 28, 2008

**The Agreement and General Conditions dated May 25, 2005 have been updated from versions that were formally adopted and in use prior to this date. The changes made to the General Conditions are identified in a document entitled Revisions to General Conditions that is available on DFCM's web site at <http://dfcm.utah.gov>**

## NOTICE TO CONTRACTORS

Sealed bids will be received by the Division of Facilities Construction and Management (DFCM) for:

**RANDALL JONES THEATER: THEATRICAL LIGHTING AND DIMMING SYSTEM**  
**SOUTHERN UTAH UNIVERSITY – CEDAR CITY, UTAH**  
**DFCM PROJECT NO: 08108730**

Bids will be in accordance with the Contract Documents that will be available on **Wednesday, October 29, 2008**, and distributed in electronic format only on CDs from DFCM, 4110 State Office Building, Salt Lake City, Utah and on the DFCM web page at <http://dfcm.utah.gov>. For questions regarding this project, please contact Jeff Reddoor, DFCM, at 801-971-9830. No others are to be contacted regarding this bidding process. The construction estimate for this project is \$300,000.00.

A **mandatory** pre-bid meeting will be held at **1:30 PM on Wednesday, November 5, 2008** at SUU-Facility Building, 351 w. University Blvd. ,Cedar City, Utah. All bidders wishing to bid on this project are required to attend this meeting.

Bids will be received until the hour of **2:00 PM on Monday, November 17, 2008** at DFCM, 4110 State Office Building, Salt Lake City, Utah 84114. Bids will be opened and read aloud in the DFCM Conference Room, 4110 State Office Building, Salt Lake City, Utah. NOTE: Bids must be received at 4110 State Office Building by the specified time.

A bid bond in the amount of five percent (5%) of the bid amount, made payable to the Division of Facilities Construction and Management on DFCM's bid bond form, shall accompany the bid.

The Division of Facilities Construction and Management reserves the right to reject any or all bids or to waive any formality or technicality in any bid in the interest of DFCM.

DIVISION OF FACILITIES CONSTRUCTION AND MANAGEMENT  
Joanna Reese, Contract Coordinator  
4110 State Office Building, Salt Lake City, Utah 84114

## **PROJECT DESCRIPTION**

Replace failed theatrical lighting and dimming systems as per engineering analysis. This included all wiring dimmer switches and related lighting components.

**PROJECT SCHEDULE**

| <b>PROJECT NAME: THEATER LIGHTING AND DIMMING SYSTEM</b> |            |                   |             |   |
|--|------------|-------------------|-------------|---|
| <b>SOUTHERN UTAH UNIVERSITY – CEDAR CITY, UTAH</b>       |            |                   |             |   |
| <b>DFCM PROJECT NO. 08108730</b>                         |            |                   |             |   |
| <b>Event</b>   | <b>Day</b> | <b>Date</b>       | <b>Time</b> | <b>Place</b>  |
| Bidding Documents Available                              | Wednesday  | October 29, 2008  | 10:00 AM    | DFCM<br>4110 State Office Bldg<br>SLC, UT and the DFCM<br>web site *      |
| <b>Mandatory</b> Pre-bid Site Meeting                    | Wednesday  | November 5, 2008  | 1:30 PM     | SUU-Facilities Bldg.<br>351 W. University Blvd.<br>Cedar City, Utah 84720 |
| Last Day to Submit Questions                             | Monday     | November 10, 2008 | 4:00 PM     | Jeff Reddoor – DFCM<br>E-mail<br>jreddoor@utah.gov                        |
| Addendum Deadline (exception for bid delays)             | Thursday   | November 13, 2008 | 2:00 PM     | DFCM web site *   |
| Prime Contractors Turn In Bid and Bid Bond               | Monday     | November 17, 2008 | 2:00 PM     | DFCM<br>4110 State Office Bldg<br>SLC, UT                                 |
| Sub-contractor List Due                                  | Tuesday    | November 18, 2008 | 2:00 PM     | DFCM<br>4110 State Office Bldg<br>SLC, UT<br>Fax 801-538-3677             |
| Substantial Completion Date                              | Friday     | February 13, 2008 | 5:00 PM     |   |

\* NOTE: DFCM's web site address is <http://dfcm.utah.gov>



## BID FORM

NAME OF BIDDER \_\_\_\_\_ DATE \_\_\_\_\_

To the Division of Facilities Construction and Management  
4110 State Office Building  
Salt Lake City, Utah 84114

The undersigned, responsive to the "Notice to Contractors" and in accordance with the "Instructions to Bidders", in compliance with your invitation for bids for the **Randall Jones Theater Lighting and Dimming System – Southern Utah University – Cedar City, Utah – DFCM Project No. 08108730** and having examined the Contract Documents and the site of the proposed Work and being familiar with all of the conditions surrounding the construction of the proposed Project, including the availability of labor, hereby proposes to furnish all labor, materials and supplies as required for the Work in accordance with the Contract Documents as specified and within the time set forth and at the price stated below. This price is to cover all expenses incurred in performing the Work required under the Contract Documents of which this bid is a part:

I/We acknowledge receipt of the following Addenda: \_\_\_\_\_

For all work shown on the Drawings and described in the Specifications and Contract Documents, I/we agree to perform for the sum of:

\_\_\_\_\_ DOLLARS (\$ \_\_\_\_\_)

(In case of discrepancy, written amount shall govern)

I/We guarantee that the Work will be Substantially Complete by February 13, 2009, should I/we be the successful bidder, and agree to pay liquidated damages in the amount of **\$ 500.00** per day for each day after expiration of the Contract Time as stated in Article 3 of the Contractor's Agreement.

This bid shall be good for 45 days after bid opening.

Enclosed is a 5% bid bond, as required, in the sum of \_\_\_\_\_

The undersigned Contractor's License Number for Utah is \_\_\_\_\_.

Upon receipt of notice of award of this bid, the undersigned agrees to execute the contract within ten (10) days, unless a shorter time is specified in the Contract Documents, and deliver acceptable Performance and Payment bonds in the prescribed form in the amount of 100% of the Contract Sum for faithful performance of the contract.

The Bid Bond attached, in the amount not less than five percent (5%) of the above bid sum, shall become the property of the Division of Facilities Construction and Management as liquidated damages for delay and additional expense caused thereby in the event that the contract is not executed and/or acceptable 100% Performance and Payment bonds are not delivered within the time set forth.

Type of Organization:

\_\_\_\_\_  
(Corporation, Partnership, Individual, etc.)

Any request and information related to Utah Preference Laws:

\_\_\_\_\_

Respectfully submitted,

\_\_\_\_\_  
Name of Bidder

ADDRESS:

\_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_  
Authorized Signature

# INSTRUCTIONS TO BIDDERS

## 1. Drawings and Specifications, Other Contract Documents

Drawings and Specifications, as well as other available Contract Documents, may be obtained as stated in the Invitation to Bid.

## 2. Bids

Before submitting a bid, each contractor shall carefully examine the Contract Documents, shall visit the site of the Work; shall fully inform themselves as to all existing conditions and limitations; and shall include in the bid the cost of all items required by the Contract Documents. If the bidder observes that portions of the Contract Documents are at variance with applicable laws, building codes, rules, regulations or contain obvious erroneous or uncoordinated information, the bidder shall promptly notify the DFCM Representative and the necessary changes shall be accomplished by Addendum.

The bid, bearing original signatures, must be typed or handwritten in ink on the Bid Form provided in the procurement documents and submitted in a sealed envelope at the location specified by the Invitation to Bid prior to the deadline for submission of bids.

Bid bond security, in the amount of five percent (5%) of the bid, made payable to the Division of Facilities Construction and Management, shall accompany bid. **THE BID BOND MUST BE ON THE BID BOND FORM PROVIDED IN THE PROCUREMENT DOCUMENTS IN ORDER TO BE CONSIDERED AN ACCEPTABLE BID.**

If the bid bond security is submitted on a bid bond form other than DFCM's required bid bond form, and the bid security meets all other legal requirements, the bidder will be allowed to provide an acceptable bid bond by the close of business on the next business day following notification by DFCM of submission of a defective bid bond security. **NOTE: A cashier's check cannot be used as a substitute for a bid bond.**

## 3. Contract and Bond

The Contractor's Agreement will be in the form found in the specifications. The Contract Time will be as indicated in the bid. The successful bidder, simultaneously with the execution of the Contract Agreement, will be required to furnish a performance bond and a payment bond, both bearing original signatures, upon the forms provided in the procurement documents. The performance and payment bonds shall be for an amount equal to one hundred percent (100%) of the contract sum and secured from a company that meets the requirements specified in the requisite forms. Any bonding requirements for subcontractors will be specified in the Supplementary General Conditions.

**4. Listing of Subcontractors**

Listing of Subcontractors shall be as summarized in the “Instructions and Subcontractor’s List Form”, which are included as part of these Contract Documents. The Subcontractors List shall be delivered to DFCM or faxed to DFCM at (801)538-3677 within 24 hours of the bid opening. Requirements for listing additional subcontractors will be listed in the Contract Documents.

DFCM retains the right to audit or take other steps necessary to confirm compliance with requirements for the listing and changing of subcontractors. Any contractor who is found to not be in compliance with these requirements is subject to a debarment hearing and may be debarred from consideration for award of contracts for a period of up to three years.

**5. Interpretation of Drawings and Specifications**

If any person or entity contemplating submitting a bid is in doubt as to the meaning of any part of the drawings, specifications or other Contract Documents, such person shall submit to the DFCM Project Manager a request for an interpretation thereof. The person or entity submitting the request will be responsible for its prompt delivery. Any interpretation of the proposed documents will be made only by addenda posted on DFCM’s web site at <http://dfcm.utah.gov>. Neither the DFCM nor A/E will be responsible for any other explanations or interpretations of the proposed documents. A/E shall be deemed to refer to the architect or engineer hired by DFCM as the A/E or Consultant for the Project.

**6. Addenda**

Addenda will be posted on DFCM’s web site at <http://dfcm.utah.gov>. Contractors are responsible for obtaining information contained in each addendum from the web site. Addenda issued prior to the submittal deadline shall become part of the bidding process and must be acknowledged on the bid form. Failure to acknowledge addenda may result in disqualification from bidding.

**7. Award of Contract**

The Contract will be awarded as soon as possible to the lowest, responsive and responsible bidder, based on the lowest combination of base bid and acceptable prioritized alternates, provided the bid is reasonable, is in the interests of the State of Utah to accept and after applying the Utah Preference Laws in U.C.A. Title 63, Chapter 56. DFCM reserves the right to waive any technicalities or formalities in any bid or in the bidding. Alternates will be accepted on a prioritized basis with Alternate 1 being highest priority, Alternate 2 having second priority, etc.

**8. DFCM Contractor Performance Rating**

As a contractor completes each DFCM project, DFCM, the architect/engineer and the using agency will evaluate project performance based on the enclosed “DFCM Contractor Performance Rating” form. The ratings issued on this project will not affect this project but may affect the award on future projects.

**9. Licensure**

The Contractor shall comply with and require all of its subcontractors to comply with the license laws as required by the State of Utah.

**10. Permits**

In concurrence with the requirements for permitting in the General Conditions, it is the responsibility of the Contractor to obtain the fugitive dust plan requirements from the Utah Division of Air Quality and the SWPPP requirements from the Utah Department of Environmental Quality and submit the completed forms and pay any permit fee that may be required for this specific project. Failure to obtain the required permit may result in work stoppage and/or fines from the regulating authority that will be the sole responsibility of the Contractor. Any delay to the project as a result of any such failure to obtain the permit or noncompliance with the permit shall not be eligible for any extension in the Contract Time.

**11. Right to Reject Bids**

DFCM reserves the right to reject any or all Bids.

**12. Time is of the Essence**

Time is of the essence in regard to all the requirements of the Contract Documents.

**13. Withdrawal of Bids**

Bids may be withdrawn on written request received from bidder prior to the time fixed for opening. Negligence on the part of the bidder in preparing the bid confers no right for the withdrawal of the bid after it has been opened.

**14. Product Approvals**

Where reference is made to one or more proprietary products in the Contract Documents, but restrictive descriptive materials of one or more manufacturer(s) is referred to in the Contract Documents, the products of other manufacturers will be accepted, provided they equal or exceed the standards set forth in the drawings and specifications and are compatible with the intent and purpose of

the design, subject to the written approval of the A/E. Such written approval must occur prior to the deadline established for the last scheduled addenda to be issued. The A/E's written approval will be in an issued addendum. If the descriptive material is not restrictive, the products of other manufacturers specified will be accepted without prior approval provided they are compatible with the intent and purpose of the design as determined by the A/E.

**15. Financial Responsibility of Contractors, Subcontractors and Sub-subcontractors**

Contractors shall respond promptly to any inquiry in writing by DFCM to any concern of financial responsibility of the contractor, subcontractor or sub-subcontractor.

**16. Debarment**

By submitting a bid, the Contractor certifies that neither it nor its principals, including project and site managers, have been, or are under consideration for, debarment or suspension, or any action that would exclude such from participation in a construction contract by any governmental department or agency. If the Contractor cannot certify this statement, attach to the bid a detailed written explanation which must be reviewed and approved by DFCM as part of the requirements for award of the Project.

**BID BOND**

(Title 63, Chapter 56, U. C. A. 1953, as Amended)

**KNOW ALL PERSONS BY THESE PRESENTS:**

That \_\_\_\_\_ hereinafter referred to as the "Principal," and \_\_\_\_\_, a corporation organized and existing under the laws of the State of \_\_\_\_\_, with its principal office in the City of \_\_\_\_\_ and authorized to transact business in this State and U. S. Department of the Treasury Listed, (Circular 570, Companies Holding Certificates of Authority as Acceptable Securities on Federal Bonds and as Acceptable Reinsuring Companies); hereinafter referred to as the "Surety," are held and firmly bound unto the STATE OF UTAH, hereinafter referred to as the "Obligee," in the amount of \$ \_\_\_\_\_ (5% of the accompanying bid), being the sum of this Bond to which payment the Principal and Surety bind themselves, their heirs, executors, administrators, successors and assigns, jointly and severally, firmly by these presents.

**THE CONDITION OF THIS OBLIGATION IS SUCH** that whereas the Principal has submitted to Obligee the accompanying bid incorporated by reference herein, dated as shown, to enter into a contract in writing for the \_\_\_\_\_ Project.

**NOW, THEREFORE, THE CONDITION OF THE ABOVE OBLIGATION IS SUCH**, that if the said principal does not execute a contract and give bond to be approved by the Obligee for the faithful performance thereof within ten (10) days after being notified in writing of such contract to the principal, then the sum of the amount stated above will be forfeited to the State of Utah as liquidated damages and not as a penalty; if the said principal shall execute a contract and give bond to be approved by the Obligee for the faithful performance thereof within ten (10) days after being notified in writing of such contract to the Principal, then this obligation shall be null and void. It is expressly understood and agreed that the liability of the Surety for any and all defaults of the Principal hereunder shall be the full penal sum of this Bond. The Surety, for value received, hereby stipulates and agrees that obligations of the Surety under this Bond shall be for a term of sixty (60) days from actual date of the bid opening.

**PROVIDED, HOWEVER**, that this Bond is executed pursuant to provisions of Title 63, Chapter 56, Utah Code Annotated, 1953, as amended, and all liabilities on this Bond shall be determined in accordance with said provisions to same extent as if it were copied at length herein.

**IN WITNESS WHEREOF**, the above bounden parties have executed this instrument under their several seals on the date indicated below, the name and corporate seal of each corporate party being hereto affixed and these presents duly signed by its undersigned representative, pursuant to authority of its governing body.

**DATED** this \_\_\_\_\_ day of \_\_\_\_\_, 20\_\_\_\_\_.

**Principal's name and address (if other than a corporation):**

\_\_\_\_\_  
\_\_\_\_\_

By: \_\_\_\_\_

Title: \_\_\_\_\_

**Principal's name and address (if a corporation):**

\_\_\_\_\_  
\_\_\_\_\_

By: \_\_\_\_\_

Title: \_\_\_\_\_

(Affix Corporate Seal)

**Surety's name and address:**

\_\_\_\_\_  
\_\_\_\_\_

By: \_\_\_\_\_

Attorney-in-Fact (Affix Corporate Seal)

STATE OF \_\_\_\_\_ )  
 ) ss.  
COUNTY OF \_\_\_\_\_ )

On this \_\_\_ day of \_\_\_\_\_, 20\_\_\_\_, personally appeared before me \_\_\_\_\_, whose identity is personally known to me or proved to me on the basis of satisfactory evidence, and who, being by me duly sworn, did say that he/she is the Attorney-in-fact of the above-named Surety Company, and that he/she is duly authorized to execute the same and has complied in all respects with the laws of Utah in reference to becoming sole surety upon bonds, undertakings and obligations, and that he/she acknowledged to me that as Attorney-in-fact executed the same.

Subscribed and sworn to before me this \_\_\_\_\_ day of \_\_\_\_\_, 20\_\_\_\_\_.

My Commission Expires: \_\_\_\_\_

Resides at: \_\_\_\_\_

\_\_\_\_\_  
NOTARY PUBLIC

**Agency:** \_\_\_\_\_  
**Agent:** \_\_\_\_\_  
**Address:** \_\_\_\_\_  
**Phone:** \_\_\_\_\_

Approved As To Form: May 25, 2005  
By Alan S. Bachman, Asst Attorney General



**Division of Facilities Construction and**

**INSTRUCTIONS AND SUBCONTRACTORS LIST FORM**

The three low bidders, as well as all other bidders that desire to be considered, are required by law to submit to DFCM within 24 hours of bid opening a list of **ALL** first-tier subcontractors, including the subcontractor's name, bid amount and other information required by Building Board Rule and as stated in these Contract Documents, based on the following:

**DOLLAR AMOUNTS FOR LISTING**

**PROJECTS UNDER \$500,000: ALL FIRST-TIER SUBS \$20,000 OR OVER MUST BE LISTED**  
**PROJECTS \$500,000 OR MORE: ALL FIRST-TIER SUBS \$35,000 OR OVER MUST BE LISTED**

- Any additional subcontractors identified in the bid documents shall also be listed.
- The DFCM Director may not consider any bid submitted by a bidder if the bidder fails to submit a subcontractor list meeting the requirements of State law.
- List subcontractors for base bid as well as the impact on the list that the selection of any alternate may have.
- Bidder may not list more than one subcontractor to perform the same work.
- If there are no subcontractors for the job that are required to be reported by State law (either because there are no subcontractors that will be used on the project or because there are no first-tier subcontractors over the dollar amounts referred to above), then you do not need to submit a sublist. If you do not submit a sublist, it will be deemed to be a representation by you that there are no subcontractors on the job that are required to be reported under State law. At any time, DFCM reserves the right to inquire, for security purposes, as to the identification of the subcontractors at any tier that will be on the worksite.

**LICENSURE:**

The subcontractor's name, the type of work, the subcontractor's bid amount, and the subcontractor's license number as issued by DOPL, if such license is required under Utah Law, shall be listed. Bidder shall certify that all subcontractors, required to be licensed, are licensed as required by State law. A subcontractor includes a trade contractor or specialty contractor and does not include suppliers who provide only materials, equipment, or supplies to a contractor or subcontractor.

**'SPECIAL EXCEPTION':**

A bidder may list 'Special Exception' in place of a subcontractor when the bidder intends to obtain a subcontractor to perform the work at a later date because the bidder was unable to obtain a qualified or reasonable bid under the provisions of U.C.A. Section 63A-5-208(4). The bidder shall insert the term 'Special Exception' for that category of work, and shall provide documentation with the subcontractor list describing the bidder's efforts to obtain a bid of a qualified subcontractor at a reasonable cost and why the bidder was unable to obtain a qualified subcontractor bid. The Director must find that the bidder complied in good faith with State law requirements for any 'Special Exception' designation, in order for the bid to be considered. If awarded the contract, the Director shall supervise the bidder's efforts to obtain a qualified subcontractor bid. The amount of the awarded contract may not be adjusted to reflect the actual amount of the subcontractor's bid. Any listing of 'Special Exception' on the sublist form shall also include amount allocated for that work.

**GROUNDS FOR DISQUALIFICATION:**

The Director may not consider any bid submitted by a bidder if the bidder fails to submit a subcontractor list meeting the requirements of State law. Director may withhold awarding the contract to a particular bidder if one or more of the proposed subcontractors are considered by the Director to be unqualified to do the Work or for

**INSTRUCTIONS AND SUBCONTRACTORS LIST FORM**  
**Page No. 2**

such other reason in the best interest of the State of Utah. Notwithstanding any other provision in these instructions, if there is a good faith error on the sublist form, at the sole discretion of the Director, the Director may provide notice to the contractor and the contractor shall have 24 hours to submit the correction to the Director. If such correction is submitted timely, then the sublist requirements shall be considered met.

**CHANGES OF SUBCONTRACTORS SPECIFICALLY IDENTIFIED ON SUBLIST FORM:**

Subsequent to twenty-four hours after the bid opening, the contractor may change its listed subcontractors only after receiving written permission from the Director based on complying with all of the following criteria.

- (1) The contractor has established in writing that the change is in the best interest of the State and that the contractor establishes an appropriate reason for the change, which may include, but not is not limited to, the following reasons: the original subcontractor has failed to perform, or is not qualified or capable of performing, and/or the subcontractor has requested in writing to be released.
- (2) The circumstances related to the request for the change do not indicate any bad faith in the original listing of the subcontractors.
- (3) Any requirement set forth by the Director to ensure that the process used to select a new subcontractor does not give rise to bid shopping.
- (4) Any increase in the cost of the subject subcontractor work is borne by the contractor.
- (5) Any decrease in the cost of the subject subcontractor work shall result in a deductive change order being issued for the contract for such decreased amount.
- (6) The Director will give substantial weight to whether the subcontractor has consented in writing to being removed unless the Contractor establishes that the subcontractor is not qualified for the work.

**EXAMPLE:**

Example of a list where there are only four subcontractors:

| TYPE OF WORK            | SUBCONTRACTOR, "SELF" OR "SPECIAL EXCEPTION" | SUBCONTRACTOR BID AMOUNT | CONTRACTOR LICENSE #                           |
|-------------------------|--|--------------------------|--|
| ELECTRICAL              | ABCD Electric Inc.                           | \$350,000.00             | 123456789000                                   |
| LANDSCAPING             | "Self" *                                     | \$300,000.00             | 123456789000                                   |
| CONCRETE (ALTERNATE #1) | XYZ Concrete Inc                             | \$298,000.00             | 987654321000                                   |
| MECHANICAL              | "Special Exception" (attach documentation)   | Fixed at: \$350,000.00   | (TO BE PROVIDED AFTER OBTAINING SUBCONTRACTOR) |

\* Bidders may list "self", but it is not required.

**PURSUANT TO STATE LAW - SUBCONTRACTOR BID AMOUNTS CONTAINED IN THIS SUBCONTRACTOR LIST SHALL NOT BE DISCLOSED UNTIL THE CONTRACT HAS BEEN AWARDED.**



SUBCONTRACTORS LIST
FAX TO 801-538-3677

PROJECT TITLE: \_\_\_\_\_

Caution: You must read and comply fully with instructions.

Table with 4 columns: TYPE OF WORK, SUBCONTRACTOR, 'SELF' OR 'SPECIAL EXCEPTION', SUBCONTRACTOR BID AMOUNT, CONT. LICENSE #. The table contains 15 empty rows for data entry.

We certify that:

- 1. This list includes all subcontractors as required by the instructions, including those related to the base bid as well as any alternates.
2. We have listed 'Self' or 'Special Exception' in accordance with the instructions.
3. All subcontractors are appropriately licensed as required by State law.

FIRM: \_\_\_\_\_

DATE: \_\_\_\_\_

SIGNED BY: \_\_\_\_\_

NOTICE: FAILURE TO SUBMIT THIS FORM, PROPERLY COMPLETED AND SIGNED, AS REQUIRED IN THESE CONTRACT DOCUMENTS, SHALL BE GROUNDS FOR OWNER'S REFUSAL TO ENTER INTO A WRITTEN CONTRACT WITH BIDDER. ACTION MAY BE TAKEN AGAINST BIDDERS BID BOND AS DEEMED APPROPRIATE BY OWNER. ATTACH A SECOND PAGE IF NECESSARY.

**CONTRACTOR'S AGREEMENT**

FOR:

\_\_\_\_\_  
\_\_\_\_\_  
\_\_\_\_\_

THIS CONTRACTOR'S AGREEMENT, made and entered into this \_\_\_\_ day of \_\_\_\_\_, 20\_\_, by and between the DIVISION OF FACILITIES CONSTRUCTION AND MANAGEMENT, hereinafter referred to as "DFCM", and \_\_\_\_\_, incorporated in the State of \_\_\_\_\_ and authorized to do business in the State of Utah, hereinafter referred to as "Contractor", whose address is \_\_\_\_\_.

WITNESSETH: WHEREAS, DFCM intends to have Work performed at \_\_\_\_\_.

WHEREAS, Contractor agrees to perform the Work for the sum stated herein.

NOW, THEREFORE, DFCM and Contractor for the consideration provided in this Contractor's Agreement, agree as follows:

**ARTICLE 1. SCOPE OF WORK.** The Work to be performed shall be in accordance with the Contract Documents prepared by \_\_\_\_\_ and entitled "\_\_\_\_\_."

The DFCM General Conditions ("General Conditions") dated May 25, 2005 and Supplemental General Conditions dated July 15, 2008 ("also referred to as General Conditions") on file at the office of DFCM and available on the DFCM website, are hereby incorporated by reference as part of this Agreement and are included in the specifications for this Project. All terms used in this Contractor's Agreement shall be as defined in the Contract Documents, and in particular, the General Conditions.

The Contractor Agrees to furnish labor, materials and equipment to complete the Work as required in the Contract Documents which are hereby incorporated by reference. It is understood and agreed by the parties hereto that all Work shall be performed as required in the Contract Documents and shall be subject to inspection and approval of DFCM or its authorized representative. The relationship of the Contractor to the DFCM hereunder is that of an independent Contractor.

**ARTICLE 2. CONTRACT SUM.** The DFCM agrees to pay and the Contractor agrees to accept in full performance of this Contractor's Agreement, the sum of \_\_\_\_\_ DOLLARS AND NO CENTS (\$\_\_\_\_\_.00), which is the base bid, and which sum also includes the cost of a 100% Performance Bond and a 100%

CONTRACTOR'S AGREEMENT  
PAGE NO. 2

Payment Bond as well as all insurance requirements of the Contractor. Said bonds have already been posted by the Contractor pursuant to State law. The required proof of insurance certificates have been delivered to DFCM in accordance with the General Conditions before the execution of this Contractor's Agreement.

**ARTICLE 3. TIME OF COMPLETION AND DELAY REMEDY.** The Work shall be Substantially Complete by \_\_\_\_\_. Contractor agrees to pay liquidated damages in the amount of \$\_\_\_\_\_ per day for each day after expiration of the Contract Time until the Contractor achieves Substantial Completion in accordance with the Contract Documents, if Contractor's delay makes the damages applicable. The provision for liquidated damages is: (a) to compensate the DFCM for delay only; (b) is provided for herein because actual damages can not be readily ascertained at the time of execution of this Contractor's Agreement; (c) is not a penalty; and (d) shall not prevent the DFCM from maintaining Claims for other non-delay damages, such as costs to complete or remedy defective Work.

No action shall be maintained by the Contractor, including its or Subcontractor or suppliers at any tier, against the DFCM or State of Utah for damages or other claims due to losses attributable to hindrances or delays from any cause whatsoever, including acts and omissions of the DFCM or its officers, employees or agents, except as expressly provided in the General Conditions. The Contractor may receive a written extension of time, signed by the DFCM, in which to complete the Work under this Contractor's Agreement in accordance with the General Conditions.

**ARTICLE 4. CONTRACT DOCUMENTS.** The Contract Documents consist of this Contractor's Agreement, the Conditions of the Contract (DFCM General Conditions, Supplementary and other Conditions), the Drawings, Specifications, Addenda and Modifications. The Contract Documents shall also include the bidding documents, including the Invitation to Bid, Instructions to Bidders/ Proposers and the Bid/Proposal, to the extent not in conflict therewith and other documents and oral presentations that are documented as an attachment to the contract.

All such documents are hereby incorporated by reference herein. Any reference in this Contractor's Agreement to certain provisions of the Contract Documents shall in no way be construed as to lessen the importance or applicability of any other provisions of the Contract Documents.

**ARTICLE 5. PAYMENT.** The DFCM agrees to pay the Contractor from time to time as the Work progresses, but not more than once each month after the date of Notice to Proceed, and only upon Certificate of the A/E for Work performed during the preceding calendar month, ninety-five percent (95%) of the value of the labor performed and ninety-five percent (95%) of the value of materials furnished in place or on the site. The Contractor agrees to furnish to the DFCM invoices for materials purchased and on the site but not installed, for which the Contractor requests payment and agrees to

safeguard and protect such equipment or materials and is responsible for safekeeping thereof and if such be stolen, lost or destroyed, to replace same.

Such evidence of labor performed and materials furnished as the DFCM may reasonably require shall be supplied by the Contractor at the time of request for Certificate of Payment on account. Materials for which payment has been made cannot be removed from the job site without DFCM's written approval. Five percent (5%) of the earned amount shall be retained from each monthly payment. The retainage, including any additional retainage imposed and the release of any retainage, shall be in accordance with UCA 13-8-5 as amended. Contractor shall also comply with the requirements of UCA 13-8-5, including restrictions of retainage regarding subcontractors and the distribution of interest earned on the retention proceeds. The DFCM shall not be responsible for enforcing the Contractor's obligations under State law in fulfilling the retention law requirements with subcontractors at any tier.

**ARTICLE 6. INDEBTEDNESS.** Before final payment is made, the Contractor must submit evidence satisfactory to the DFCM that all payrolls, materials bills, subcontracts at any tier and outstanding indebtedness in connection with the Work have been properly paid. Final Payment will be made after receipt of said evidence, final acceptance of the Work by the DFCM as well as compliance with the applicable provisions of the General Conditions.

Contractor shall respond immediately to any inquiry in writing by DFCM as to any concern of financial responsibility and DFCM reserves the right to request any waivers, releases or bonds from Contractor in regard to any rights of Subcontractors (including suppliers) at any tier or any third parties prior to any payment by DFCM to Contractor.

**ARTICLE 7. ADDITIONAL WORK.** It is understood and agreed by the parties hereto that no money will be paid to the Contractor for additional labor or materials furnished unless a new contract in writing or a Modification hereof in accordance with the General Conditions and the Contract Documents for such additional labor or materials has been executed. The DFCM specifically reserves the right to modify or amend this Contractor's Agreement and the total sum due hereunder either by enlarging or restricting the scope of the Work.

**ARTICLE 8. INSPECTIONS.** The Work shall be inspected for acceptance in accordance with the General Conditions.

**ARTICLE 9. DISPUTES.** Any dispute, PRE or Claim between the parties shall be subject to the provisions of Article 7 of the General Conditions. DFCM reserves all rights to pursue its rights and remedies as provided in the General Conditions.

**ARTICLE 10. TERMINATION, SUSPENSION OR ABANDONMENT.** This Contractor's Agreement may be terminated, suspended or abandoned in accordance with the General Conditions.

**ARTICLE 11. DFCM'S RIGHT TO WITHHOLD CERTAIN AMOUNT AND MAKE USE THEREOF.** The DFCM may withhold from payment to the Contractor such amount as, in DFCM's judgment, may be necessary to pay just claims against the Contractor or Subcontractor at any tier for labor and services rendered and materials furnished in and about the Work. The DFCM may apply such withheld amounts for the payment of such claims in DFCM's discretion. In so doing, the DFCM shall be deemed the agent of Contractor and payment so made by the DFCM shall be considered as payment made under this Contractor's Agreement by the DFCM to the Contractor. DFCM shall not be liable to the Contractor for any such payment made in good faith. Such withholdings and payments may be made without prior approval of the Contractor and may be also be prior to any determination as a result of any dispute, PRE, Claim or litigation.

**ARTICLE 12. INDEMNIFICATION.** The Contractor shall comply with the indemnification provisions of the General Conditions.

**ARTICLE 13. SUCCESSORS AND ASSIGNMENT OF CONTRACT.** The DFCM and Contractor, respectively bind themselves, their partners, successors, assigns and legal representatives to the other party to this Agreement, and to partners, successors, assigns and legal representatives of such other party with respect to all covenants, provisions, rights and responsibilities of this Contractor's Agreement. The Contractor shall not assign this Contractor's Agreement without the prior written consent of the DFCM, nor shall the Contractor assign any moneys due or to become due as well as any rights under this Contractor's Agreement, without prior written consent of the DFCM.

**ARTICLE 14. RELATIONSHIP OF THE PARTIES.** The Contractor accepts the relationship of trust and confidence established by this Contractor's Agreement and covenants with the DFCM to cooperate with the DFCM and A/E and use the Contractor's best skill, efforts and judgment in furthering the interest of the DFCM; to furnish efficient business administration and supervision; to make best efforts to furnish at all times an adequate supply of workers and materials; and to perform the Work in the best and most expeditious and economic manner consistent with the interests of the DFCM.

**ARTICLE 15. AUTHORITY TO EXECUTE AND PERFORM AGREEMENT.** Contractor and DFCM each represent that the execution of this Contractor's Agreement and the performance thereunder is within their respective duly authorized powers.

**ARTICLE 16. ATTORNEY FEES AND COSTS.** Except as otherwise provided in the dispute resolution provisions of the General Conditions, the prevailing party shall be entitled to reasonable attorney fees and costs incurred in any action in the District Court and/or appellate body to enforce this Contractor's Agreement or recover damages or any other action as a result of a breach thereof.



**PERFORMANCE BOND**  
(Title 63, Chapter 56, U. C. A. 1953, as Amended)

That \_\_\_\_\_ hereinafter referred to as the "Principal" and \_\_\_\_\_, a corporation organized and existing under the laws of the State of \_\_\_\_\_, with its principal office in the City of \_\_\_\_\_ and authorized to transact business in this State and U. S. Department of the Treasury Listed (Circular 570, Companies Holding Certificates of Authority as Acceptable Securities on Federal Bonds and as Acceptable Reinsuring Companies); hereinafter referred to as the "Surety," are held and firmly bound unto the State of Utah, hereinafter referred to as the "Obligee," in the amount of \_\_\_\_\_ DOLLARS (\$ \_\_\_\_\_) for the payment whereof, the said Principal and Surety bind themselves and their heirs, administrators, executors, successors and assigns, jointly and severally, firmly by these presents.

**WHEREAS**, the Principal has entered into a certain written Contract with the Obligee, dated the \_\_\_\_\_ day of \_\_\_\_\_, 20\_\_\_\_, to construct \_\_\_\_\_ in the County of \_\_\_\_\_, State of Utah, Project No. \_\_\_\_\_, for the approximate sum of \_\_\_\_\_ Dollars (\$ \_\_\_\_\_), which Contract is hereby incorporated by reference herein.

**NOW, THEREFORE**, the condition of this obligation is such that if the said Principal shall faithfully perform the Contract in accordance with the Contract Documents including, but not limited to, the Plans, Specifications and conditions thereof, the one year performance warranty, and the terms of the Contract as said Contract may be subject to Modifications or changes, then this obligation shall be void; otherwise it shall remain in full force and effect.

No right of action shall accrue on this bond to or for the use of any person or corporation other than the state named herein or the heirs, executors, administrators or successors of the Owner.

The parties agree that the dispute provisions provided in the Contract Documents apply and shall constitute the sole dispute procedures of the parties.

**PROVIDED, HOWEVER**, that this Bond is executed pursuant to the Provisions of Title 63, Chapter 56, Utah Code Annotated, 1953, as amended, and all liabilities on this Bond shall be determined in accordance with said provisions to the same extent as if it were copied at length herein.

**IN WITNESS WHEREOF**, the said Principal and Surety have signed and sealed this instrument this \_\_\_\_\_ day of \_\_\_\_\_, 20\_\_\_\_.

**WITNESS OR ATTESTATION:**

\_\_\_\_\_

**PRINCIPAL:**

\_\_\_\_\_

By: \_\_\_\_\_ (Seal)

Title: \_\_\_\_\_

**WITNESS OR ATTESTATION:**

\_\_\_\_\_

**SURETY:**

\_\_\_\_\_

By: \_\_\_\_\_ (Seal)

Attorney-in-Fact

STATE OF \_\_\_\_\_ )  
 ) ss.  
COUNTY OF \_\_\_\_\_ )

On this \_\_\_\_\_ day of \_\_\_\_\_, 20\_\_\_\_, personally appeared before me \_\_\_\_\_, whose identity is personally known to me or proved to me on the basis of satisfactory evidence, and who, being by me duly sworn, did say that he/she is the Attorney in-fact of the above-named Surety Company and that he/she is duly authorized to execute the same and has complied in all respects with the laws of Utah in reference to becoming sole surety upon bonds, undertakings and obligations, and that he/she acknowledged to me that as Attorney-in-fact executed the same.

Subscribed and sworn to before me this \_\_\_\_\_ day of \_\_\_\_\_, 20\_\_\_\_.

My commission expires: \_\_\_\_\_

Resides at: \_\_\_\_\_

\_\_\_\_\_  
NOTARY PUBLIC

|                       |
|-----------------------|
| <b>Agency:</b> _____  |
| <b>Agent:</b> _____   |
| <b>Address:</b> _____ |
| <b>Phone:</b> _____   |

Approved As To Form: May 25, 2005  
By Alan S. Bachman, Asst Attorney General

**PAYMENT BOND**

(Title 63, Chapter 56, U. C. A. 1953, as Amended)

**KNOW ALL PERSONS BY THESE PRESENTS:**

That \_\_\_\_\_ hereinafter referred to as the "Principal," and \_\_\_\_\_, a corporation organized and existing under the laws of the State of \_\_\_\_\_ authorized to do business in this State and U. S. Department of the Treasury Listed (Circular 570, Companies Holding Certificates of Authority as Acceptable Securities on Federal Bonds and as Acceptable Reinsuring Companies); with its principal office in the City of \_\_\_\_\_, hereinafter referred to as the "Surety," are held and firmly bound unto the State of Utah hereinafter referred to as the "Obligee," in the amount of \_\_\_\_\_ Dollars (\$ \_\_\_\_\_) for the payment whereof, the said Principal and Surety bind themselves and their heirs, administrators, executors, successors and assigns, jointly and severally, firmly by these presents.

**WHEREAS**, the Principal has entered into a certain written Contract with the Obligee, dated the \_\_\_\_\_ day of \_\_\_\_\_, 20\_\_\_\_, to construct \_\_\_\_\_ in the County of \_\_\_\_\_, State of Utah, Project No. \_\_\_\_\_ for the approximate sum of \_\_\_\_\_ Dollars (\$ \_\_\_\_\_), which contract is hereby incorporated by reference herein.

**NOW, THEREFORE**, the condition of this obligation is such that if the said Principal shall pay all claimants supplying labor or materials to Principal or Principal's Subcontractors in compliance with the provisions of Title 63, Chapter 56, of Utah Code Annotated, 1953, as amended, and in the prosecution of the Work provided for in said Contract, then, this obligation shall be void; otherwise it shall remain in full force and effect.

That said Surety to this Bond, for value received, hereby stipulates and agrees that no changes, extensions of time, alterations or additions to the terms of the Contract or to the Work to be performed thereunder, or the specifications or drawings accompanying same shall in any way affect its obligation on this Bond, and does hereby waive notice of any such changes, extensions of time, alterations or additions to the terms of the Contract or to the Work or to the specifications or drawings and agrees that they shall become part of the Contract Documents.

**PROVIDED, HOWEVER**, that this Bond is executed pursuant to the provisions of Title 63, Chapter 56, Utah Code Annotated, 1953, as amended, and all liabilities on this Bond shall be determined in accordance with said provisions to the same extent as if it were copied at length herein.

**IN WITNESS WHEREOF**, the said Principal and Surety have signed and sealed this instrument this \_\_\_\_\_ day of \_\_\_\_\_, 20\_\_\_\_.

**WITNESS OR ATTESTATION:**

\_\_\_\_\_

**PRINCIPAL:**

\_\_\_\_\_

By: \_\_\_\_\_ (Seal)

Title: \_\_\_\_\_

**WITNESS OR ATTESTATION:**

\_\_\_\_\_

**SURETY:**

\_\_\_\_\_

By: \_\_\_\_\_ Attorney-in-Fact (Seal)

STATE OF \_\_\_\_\_ )  
 ) ss.  
COUNTY OF \_\_\_\_\_ )

On this \_\_\_\_\_ day of \_\_\_\_\_, 20\_\_\_\_, personally appeared before me \_\_\_\_\_, whose identity is personally known to me or proved to me on the basis of satisfactory evidence, and who, being by me duly sworn, did say that he/she is the Attorney-in-fact of the above-named Surety Company, and that he/she is duly authorized to execute the same and has complied in all respects with the laws of Utah in reference to becoming sole surety upon bonds, undertakings and obligations, and that he/she acknowledged to me that as Attorney-in-fact executed the same.

Subscribed and sworn to before me this \_\_\_\_\_ day of \_\_\_\_\_, 20\_\_\_\_.

My commission expires: \_\_\_\_\_  
Resides at: \_\_\_\_\_

NOTARY PUBLIC

**Agency:** \_\_\_\_\_  
**Agent:** \_\_\_\_\_  
**Address:** \_\_\_\_\_  
**Phone:** \_\_\_\_\_

Approved As To Form: May 25, 2005  
By Alan S. Bachman, Asst Attorney General



CERTIFICATE OF SUBSTANTIAL COMPLETION

PROJECT \_\_\_\_\_ PROJECT NO: \_\_\_\_\_

AGENCY/INSTITUTION \_\_\_\_\_

AREA ACCEPTED \_\_\_\_\_

The Work performed under the subject Contract has been reviewed on this date and found to be Substantially Completed as defined in the General Conditions; including that the construction is sufficiently completed in accordance with the Contract Documents, as modified by any change orders agreed to by the parties, so that the State of Utah can occupy the Project or specified area of the Project for the use for which it is intended.

The DFCM - (Owner) accepts the Project or specified area of the Project as Substantially Complete and will assume full possession of the Project or specified area of the Project at \_\_\_\_\_ (time) on \_\_\_\_\_ (date).

The DFCM accepts the Project for occupancy and agrees to assume full responsibility for maintenance and operation, including utilities and insurance, of the Project subject to the itemized responsibilities and/or exceptions noted below:

\_\_\_\_\_

The Owner acknowledges receipt of the following closeout and transition materials:

- As-built Drawings
- O & M Manuals
- Warranty Documents
- Completion of Training Requirements

A list of items to be completed or corrected (Punch List) is attached hereto. The failure to include an item on it does not alter the responsibility of the Contractor to complete all the Work in accordance with the Contract Documents, including authorized changes thereof. The amount of \_\_\_\_\_(Twice the value of the punch list work) shall be retained to assure the completion of the punch list work.


The Contractor shall complete or correct the Work on the list of (Punch List) items appended hereto within \_\_\_\_\_ calendar days from the above date of issuance of this Certificate. The amount withheld pending completion of the list of items noted and agreed to shall be: \$\_\_\_\_\_. If the list of items is not completed within the time allotted the Owner has the right to be compensated for the delays and/or complete the work with the help of independent contractor at the expense of the retained project funds. If the retained project funds are insufficient to cover the delay/completion damages, the Owner shall be promptly reimbursed for the balance of the funds needed to compensate the Owner.

\_\_\_\_\_ by: \_\_\_\_\_  
CONTRACTOR (include name of firm) (Signature) DATE

\_\_\_\_\_ by: \_\_\_\_\_  
A/E (include name of firm) (Signature) DATE

\_\_\_\_\_ by: \_\_\_\_\_  
USING INSTITUTION OR AGENCY (Signature) DATE

\_\_\_\_\_ by: \_\_\_\_\_  
DFCM (Owner) (Signature) DATE

**General Contractor Performance Rating Form**

|   |  |                           |                        |
|---|--|---------------------------|------------------------|
| Project Name:   |  | DFCM Project#             |                        |
| Contractor:<br><br>(ABC Construction, John Doe, 111-111-1111) | A/E:<br><br>(ABC Architects, Jane Doe, 222-222-2222) | Original Contract Amount: | Final Contract Amount: |
| DFCM Project Manager:   |  | Contract Date:            |                        |
| Completion Date:  |  | Date of Rating:           |                        |

| Rating Guideline        | QUALITY OF PRODUCT OR SERVICES  | COST CONTROL   | TIMELINESS OF PERFORMANCE  | BUSINESS RELATIONS   |
|-------------------------|---|--|--|--|
| <b>5-Exceptional</b>    | Contractor has demonstrated an exceptional performance level in any of the above four categories that justifies adding a point to the score. Contractor performance clearly exceeds the performance levels described as "Very Good" |  |  |  |
| <b>4-Very Good</b>      | Contractor is in compliance with contract requirements and/or delivers quality product/service.   | Contractor is effective in managing costs and submits current, accurate, and complete billings | Contractor is effective in meeting milestones and delivery schedule            | Response to inquiries, technical/service/administrative issues is effective            |
| <b>3-Satisfactory</b>   | Minor inefficiencies/errors have been identified  | Contractor is usually effective in managing cost   | Contractor is usually effective in meeting milestones and delivery schedules   | Response to inquires technical/service/administrative issues is somewhat effective     |
| <b>2-Marginal</b>       | Major problems have been encountered  | Contractor is having major difficulty managing cost effectively                                | Contractor is having major difficulty meeting milestones and delivery schedule | Response to inquiries, technical/service/administrative issues is marginally effective |
| <b>1-Unsatisfactory</b> | Contractor is not in compliance and is jeopardizing achievement of contract objectives  | Contractor is unable to manage costs effectively   | Contractor delays are jeopardizing performance of contract objectives          | Response to inquiries, technical/service/administrative issues is not effective        |

|  |              |
|--|--------------|
| <b>1. Rate Contractors quality of workmanship, management of sub contractor performance, project cleanliness, organization and safety requirement.</b> | <b>Score</b> |
| <u>Agency Comments:</u>  |              |
| <u>A &amp; E Comments:</u>   |              |
| <u>DFCM Project Manager Comments:</u>  |              |

|  |              |
|--|--------------|
| <b>2. Rate Contractor administration of project costs, change orders and financial management of the project budget.</b> | <b>Score</b> |
| <u>Agency Comments:</u>  |              |
| <u>A &amp; E Comments:</u>   |              |
| <u>DFCM Project Manager Comments:</u>  |              |

|  |              |
|--|--------------|
| <b>3. Rate Contractor's performance and adherence to Project Schedule, delay procedures and requirements of substantial completion, inspection and punch-list performance.</b> | <b>Score</b> |
| <u>Agency Comments:</u>  |              |
| <u>A &amp; E Comments:</u>   |              |
| <u>DFCM Project Manager Comments:</u>  |              |

|   |              |
|---|--------------|
| <b>4. Evaluate performance of contractor management team including project manager, engineer and superintendent also include in the rating team's ability to work well with owner, user agency and consultants.</b> | <b>Score</b> |
| <u>Agency Comments:</u>   |              |
| <u>A &amp; E Comments:</u>  |              |
| <u>DFCM Project Manager Comments:</u>   |              |

|   |       |
|---|-------|
| 5. Rate success of Contractor's management plan, completion of the plans mitigation of project risks and performance of value engineering concepts. | Score |
| <u>Agency Comments:</u>   |       |
| <u>A &amp; E Comments:</u>  |       |
| <u>DFCM Project Manager Comments:</u>   |       |

|                   |              |                   |
|-------------------|--------------|-------------------|
| <b>Signed by:</b> | <b>Date:</b> | <b>Mean Score</b> |
|-------------------|--------------|-------------------|

**Additional Comments:**



# TECHNICAL SPECIFICATIONS

Southern Utah University  
Randall L. Jones Theatre  
Cedar City, Utah

Released:  
October 24, 2008

---

## **Spectrum Engineers**

Mechanical Engineering ♦ Electrical Engineering ♦ Technology Design ♦ Lighting Design ♦ Theater Design  
Acoustical Engineering ♦ Building Commissioning ♦ Power Engineering

175 South Main Street, Suite 300, Salt Lake City, Utah 84111  
801-328-5151 ♦ 800-678-7077 ♦ FAX 801-328-5155

[www.spectrum-engineers.com](http://www.spectrum-engineers.com)

# **TECHNICAL SPECIFICATIONS**

RANDALL JONES THEATRE  
SOUTHERN UTAH UNIVERSITY  
CEDAR CITY, UTAH

LIGHTING CONTROL AND DIMMING  
REPLACEMENT PROJECT

August 28, 2008

**PREPARED BY:**

SPECTRUM ENGINEERS, INC.  
175 SOUTH MAIN, SUITE 300  
SALT LAKE CITY, UT 84111  
801 328-5151  
800 678-7077  
Joseph Good, Project Manager  
801 401-8465  
[jmg@spectrum-engineers.com](mailto:jmg@spectrum-engineers.com)

| Division | Section Title |
|----------|---------------|
|----------|---------------|

## SPECIFICATIONS GROUP

### DIVISION 26 - ELECTRICAL

|        |   |
|--------|---|
| 260500 | COMMON WORK RESULTS FOR ELECTRICAL                    |
| 260519 | LOW-VOLTAGE ELECTRICAL POWER CONDUCTORS AND CABLES    |
| 260526 | GROUNDING AND BONDING FOR ELECTRICAL SYSTEMS          |
| 260533 | RACEWAY AND BOXES FOR ELECTRICAL SYSTEMS              |
| 260529 | HANGERS AND SUPPORTS FOR ELECTRICAL SYSTEMS           |
| 260548 | VIBRATION AND SEISMIC CONTROLS FOR ELECTRICAL SYSTEMS |
| 260553 | IDENTIFICATION FOR ELECTRICAL SYSTEMS                 |
| 262416 | PANELBOARDS   |
| 262726 | WIRING DEVICES  |
| 265561 | THEATRICAL LIGHTING AND EQUIPMENT                     |

SECTION 260500 - COMMON WORK RESULTS FOR ELECTRICAL

PART 1 - GENERAL

1.1 RELATED DOCUMENTS

- A. Drawings and general provisions of the Contract, including General and Supplementary Conditions and Division 01 Specification Sections, apply to this Section.

1.2 SUMMARY

- A. Section Includes:

1. Electrical equipment coordination and installation.
2. Sleeves for raceways and cables.
3. Sleeve seals.
4. Grout.
5. Common electrical installation requirements.

1.3 DEFINITIONS

- A. EPDM: Ethylene-propylene-diene terpolymer rubber.

1.4 COORDINATION

- A. Coordinate arrangement, mounting, and support of electrical equipment:

1. To allow maximum possible headroom unless specific mounting heights that reduce headroom are indicated.
2. To provide for ease of disconnecting the equipment with minimum interference to other installations.
3. To allow right of way for piping and conduit installed at required slope.
4. So connecting raceways, cables, wireways, cable trays, and busways will be clear of obstructions and of the working and access space of other equipment.

- B. Coordinate installation of required supporting devices and set sleeves in cast-in-place concrete, masonry walls, and other structural components as they are constructed.

- C. Coordinate location of access panels and doors for electrical items that are behind finished surfaces or otherwise concealed.

- D. Coordinate sleeve selection and application with selection and application of firestopping .

## PART 2 - PRODUCTS

### 2.1 SLEEVES FOR RACEWAYS AND CABLES

- A. Steel Pipe Sleeves: ASTM A 53/A 53M, Type E, Grade B, Schedule 40, galvanized steel, plain ends.
- B. Cast-Iron Pipe Sleeves: Cast or fabricated "wall pipe," equivalent to ductile-iron pressure pipe, with plain ends and integral waterstop, unless otherwise indicated.
- C. Sleeves for Rectangular Openings: Galvanized sheet steel.
  - 1. Minimum Metal Thickness:
    - a. For sleeve cross-section rectangle perimeter less than 50 inches (1270 mm) and no side more than 16 inches (400 mm), thickness shall be 0.052 inch (1.3 mm).
    - b. For sleeve cross-section rectangle perimeter equal to, or more than, 50 inches (1270 mm) and 1 or more sides equal to, or more than, 16 inches (400 mm), thickness shall be 0.138 inch (3.5 mm).

### 2.2 SLEEVE SEALS

- A. Description: Modular sealing device, designed for field assembly, to fill annular space between sleeve and raceway or cable.
  - 1. Manufacturers: Subject to compliance with requirements, provide products by one of the following:
    - a. Calpico, Inc.
    - b. Metraflex Co.
    - c. Pipeline Seal and Insulator, Inc.
  - 2. Sealing Elements: EPDM interlocking links shaped to fit surface of cable or conduit. Include type and number required for material and size of raceway or cable.
  - 3. Pressure Plates: Carbon steel. Include two for each sealing element.
  - 4. Connecting Bolts and Nuts: Carbon steel with corrosion-resistant coating of length required to secure pressure plates to sealing elements. Include one for each sealing element.

### 2.3 GROUT

- A. Nonmetallic, Shrinkage-Resistant Grout: ASTM C 1107, factory-packaged, nonmetallic aggregate grout, noncorrosive, nonstaining, mixed with water to consistency suitable for application and a 30-minute working time.

PART 3 - EXECUTION

3.1 COMMON REQUIREMENTS FOR ELECTRICAL INSTALLATION

- A. Comply with NECA 1.
- B. Measure indicated mounting heights to bottom of unit for suspended items and to center of unit for wall-mounting items.
- C. Headroom Maintenance: If mounting heights or other location criteria are not indicated, arrange and install components and equipment to provide maximum possible headroom consistent with these requirements.
- D. Equipment: Install to facilitate service, maintenance, and repair or replacement of components of both electrical equipment and other nearby installations. Connect in such a way as to facilitate future disconnecting with minimum interference with other items in the vicinity.
- E. Right of Way: Give to piping systems installed at a required slope.

3.2 SLEEVE INSTALLATION FOR ELECTRICAL PENETRATIONS

- A. Electrical penetrations occur when raceways, cables, wireways, cable trays, or busways penetrate concrete slabs, concrete or masonry walls, or fire-rated floor and wall assemblies.
- B. Concrete Slabs and Walls: Install sleeves for penetrations unless core-drilled holes or formed openings are used. Install sleeves during erection of slabs and walls.
- C. Use pipe sleeves unless penetration arrangement requires rectangular sleeved opening.
- D. Fire-Rated Assemblies: Install sleeves for penetrations of fire-rated floor and wall assemblies unless openings compatible with firestop system used are fabricated during construction of floor or wall.
- E. Cut sleeves to length for mounting flush with both surfaces of walls.
- F. Extend sleeves installed in floors **2 inches (50 mm)** above finished floor level.
- G. Size pipe sleeves to provide **1/4-inch (6.4-mm)** annular clear space between sleeve and raceway or cable, unless indicated otherwise.
- H. Seal space outside of sleeves with grout for penetrations of concrete and masonry
  - 1. Promptly pack grout solidly between sleeve and wall so no voids remain. Tool exposed surfaces smooth; protect grout while curing.
- I. Interior Penetrations of Non-Fire-Rated Walls and Floors: Seal annular space between sleeve and raceway or cable, using joint sealant appropriate for size, depth, and location of joint.

- J. Fire-Rated-Assembly Penetrations: Maintain indicated fire rating of walls, partitions, ceilings, and floors at raceway and cable penetrations. Install sleeves and seal raceway and cable penetration sleeves with firestop materials.
- K. Roof-Penetration Sleeves: Seal penetration of individual raceways and cables with flexible boot-type flashing units applied in coordination with roofing work.
- L. Aboveground, Exterior-Wall Penetrations: Seal penetrations using steel pipe sleeves and mechanical sleeve seals. Select sleeve size to allow for 1-inch (25-mm) annular clear space between pipe and sleeve for installing mechanical sleeve seals.

### 3.3 SLEEVE-SEAL INSTALLATION

- A. Install to seal exterior wall penetrations.
- B. Use type and number of sealing elements recommended by manufacturer for raceway or cable material and size. Position raceway or cable in center of sleeve. Assemble mechanical sleeve seals and install in annular space between raceway or cable and sleeve. Tighten bolts against pressure plates that cause sealing elements to expand and make watertight seal.

### 3.4 FIRESTOPPING

- A. Apply firestopping to penetrations of fire-rated floor and wall assemblies for electrical installations to restore original fire-resistance rating of assembly.

END OF SECTION 260500

SECTION 260519 - LOW-VOLTAGE ELECTRICAL POWER CONDUCTORS AND CABLES

PART 1 - GENERAL

1.1 RELATED DOCUMENTS

- A. Drawings and general provisions of the Contract, including General and Supplementary Conditions and Division 01 Specification Sections, apply to this Section.

1.2 SUMMARY

- A. This Section includes the following:
  - 1. Building wires and cables rated 600 V and less.
  - 2. Connectors, splices, and terminations rated 600 V and less.
  - 3. UTP cabling, terminations and connections
- B. Related Sections include the following:
  - 1. Division 26 Section "Medium-Voltage Cables" for single-conductor and multiconductor cables, cable splices, and terminations for electrical distribution systems with 2001 to 35,000 V.

1.3 SUBMITTALS

- A. Product Data: For each type of product indicated.

1.4 QUALITY ASSURANCE

- A. Electrical Components, Devices, and Accessories: Listed and labeled as defined in NFPA 70, Article 100, by a testing agency acceptable to authorities having jurisdiction, and marked for intended use.
- B. Comply with NFPA 70.

PART 2 - PRODUCTS

2.1 CONDUCTORS AND CABLES

- A. Manufacturers: Subject to compliance with requirements, provide products by one of the following:
  - 1. Alcan Products Corporation; Alcan Cable Division.
  - 2. American Insulated Wire Corp.; a Leviton Company.

3. General Cable Corporation.
4. Senator Wire & Cable Company.
5. Southwire Company.
6. Belden Corp.

B. Copper Conductors: Comply with NEMA WC 70.

C. Conductor Insulation: Comply with NEMA WC 70 for Types THHN-THWN-2 and XHHW-2.

## 2.2 CONNECTORS AND SPLICES

A. Manufacturers: Subject to compliance with requirements, provide products by one of the following:

1. AFC Cable Systems, Inc.
2. Hubbell Power Systems, Inc.
3. O-Z/Gedney; EGS Electrical Group LLC.
4. 3M; Electrical Products Division.
5. Tyco Electronics Corp.

B. Description: Factory-fabricated connectors and splices of size, ampacity rating, material, type, and class for application and service indicated.

## 2.3 UTP CABLE

A. Manufacturers: Subject to compliance with requirements, [provide products by one of the following] [available manufacturers offering products that may be incorporated into the Work include, but are not limited to, the following]:

1. Belden CDT Inc.; Electronics Division.
2. Berk-Tek; a Nexans company.
3. CommScope, Inc.
4. Draka USA.
5. Genesis Cable Products; Honeywell International, Inc.
6. KRONE Incorporated.
7. Mohawk; a division of Belden CDT.
8. Nordex/CDT; a subsidiary of Cable Design Technologies.
9. Superior Essex Inc.
10. SYSTIMAX Solutions; a CommScope, Inc. brand.
11. 3M.
12. Tyco Electronics/AMP Netconnect; Tyco International Ltd.

B. Description: 100-ohm, four-pair UTP[, formed into 25-pair binder groups covered with a blue thermoplastic jacket].

1. Comply with ICEA S-90-661 for mechanical properties.
2. Comply with TIA/EIA-568-B.2 Category 6.

## 2.4 UTP CABLE HARDWARE

- A. Manufacturers: Subject to compliance with requirements, [provide products by one of the following] [available manufacturers offering products that may be incorporated into the Work include, but are not limited to, the following]:
  - 1. American Technology Systems Industries, Inc.
  - 2. Dynacom Corporation.
  - 3. Hubbell Premise Wiring.
  - 4. KRONE Incorporated.
  - 5. Leviton Voice & Data Division.
  - 6. Molex Premise Networks; a division of Molex, Inc.
  - 7. Nordex/CDT; a subsidiary of Cable Design Technologies.
  - 8. Panduit Corp.
  - 9. Siemon Co. (The).
  - 10. Tyco Electronics/AMP Netconnect; Tyco International Ltd.
- B. UTP Cable Connecting Hardware: IDC type, using modules designed for punch-down caps or tools. Cables shall be terminated with connecting hardware of the same category or higher.
- C. Connecting Blocks: 110 style for Category 6. Provide blocks for the number of cables terminated on the block, plus 25 percent spare; integral with connector bodies, including plugs and jacks where indicated.

## PART 3 - EXECUTION

### 3.1 CONDUCTOR MATERIAL APPLICATIONS

- A. Feeders: Copper. Solid for No. 12 AWG and smaller; stranded for No. 10 AWG and larger.
- B. Branch Circuits: Copper. Solid for No. 12 AWG and smaller; stranded for No. 10 AWG and larger.

### 3.2 CONDUCTOR INSULATION AND MULTICONDUCTOR CABLE APPLICATIONS AND WIRING METHODS

- A. Service Entrance: Type XHHW-2, single conductors in raceway.
- B. Feeders: Type THHN-THWN, single conductors in raceway.
- C. Branch Circuits Concealed in Ceilings, Walls, and Partitions: Type THHN-THWN, single conductors in raceway.
- D. Multi-Wire Branch Circuits: Install no more than three circuits in a raceway, unless specifically shown otherwise.
  - 1. For 120V multi-wire branch circuits, provide one neutral conductor for each phase conductor.

- E. Minimum Branch Circuit Conductor Size: Provide the following minimum sizes for distances listed on 20A branch circuits to prevent excessive voltage drop. The circuit length shall be measured along the length of the conductor from the circuit breaker in the panelboard to the last device on the circuit. If required, increase raceway size to comply with conductor fill requirements of NFPA 70.
  - 1. Branch Circuit Voltage of 120V:
    - a. Circuit lengths between 0 feet and 110 feet: Provide minimum #10 AWG conductor size.
    - b. Circuit lengths between 110 feet and 170 feet: Provide minimum #8 AWG conductor size.
    - c. Circuit lengths greater than 170 feet: Perform voltage drop calculations and provide conductor size to keep branch circuit voltage drop less than 3% with a 15 amp load.
  - 2. Branch Circuit Voltage of 277V:
    - a. Circuit lengths less than 150 feet: Provide minimum #12 AWG conductor size.
    - b. Circuit lengths between 150 feet and 240 feet: Provide minimum #10 AWG conductor size.
    - c. Circuit lengths between 240 feet and 380 feet: Provide minimum #8 AWG conductor size.
    - d. Circuit lengths greater than 380 feet: Perform voltage drop calculations and provide conductor size to keep branch circuit voltage drop less than 3% with a 15 amp load.
- F. Cord Drops and Portable Appliance Connections: Type SO, hard service cord with stainless-steel, wire-mesh, strain relief device at terminations to suit application.
- G. Class 1 Control Circuits: Type THHN-THWN, in raceway.
- H. Class 2 Control Circuits: Type THHN-THWN, in raceway.

### 3.3 INSTALLATION OF CONDUCTORS AND CABLES

- A. Conceal cables in finished walls, ceilings, and floors, unless otherwise indicated.
- B. Use manufacturer-approved pulling compound or lubricant where necessary; compound used must not deteriorate conductor or insulation. Do not exceed manufacturer's recommended maximum pulling tensions and sidewall pressure values.
- C. Use pulling means, including fish tape, cable, rope, and basket-weave wire/cable grips, that will not damage cables or raceway.
- D. Install exposed cables parallel and perpendicular to surfaces of exposed structural members, and follow surface contours where possible.
- E. Support cables according to Division 26 Section "Hangers and Supports for Electrical Systems."
- F. Identify and color-code conductors and cables according to Division 26 Section "Identification for Electrical Systems."

### 3.4 CONNECTIONS

- A. Tighten electrical connectors and terminals according to manufacturer's published torque-tightening values. If manufacturer's torque values are not indicated, use those specified in UL 486A and UL 486B.
- B. Make splices and taps that are compatible with conductor material and that possess equivalent or better mechanical strength and insulation ratings than unspliced conductors.
- C. Wiring at Outlets: Install conductor at each outlet, with at least **12 inches (300 mm)** of slack.

### 3.5 FIRESTOPPING

- A. Apply firestopping to electrical penetrations of fire-rated floor and wall assemblies to restore original fire-resistance rating of assembly according to Division 07 Section "Penetration Firestopping."

### 3.6 FIELD QUALITY CONTROL

- A. Perform tests and inspections and prepare test reports.
- B. Tests and Inspections:
  - 1. After installing conductors and cables and before electrical circuitry has been energized, test service entrance and feeder conductors, and conductors feeding the following critical equipment and services for compliance with requirements.
  - 2. Perform each visual and mechanical inspection and electrical test stated in NETA Acceptance Testing Specification. Certify compliance with test parameters.
- C. Test Reports: Prepare a written report to record the following:
  - 1. Test procedures used.
  - 2. Test results that comply with requirements.
  - 3. Test results that do not comply with requirements and corrective action taken to achieve compliance with requirements.
- D. Remove and replace malfunctioning units and retest as specified above.

END OF SECTION 260519

SECTION 260526 - GROUNDING AND BONDING FOR ELECTRICAL SYSTEMS

PART 1 - GENERAL

1.1 RELATED DOCUMENTS

- A. Drawings and general provisions of the Contract, including General and Supplementary Conditions and Division 01 Specification Sections, apply to this Section.

1.2 SUMMARY

- A. This Section includes methods and materials for grounding systems and equipment.

1.3 QUALITY ASSURANCE

- A. Electrical Components, Devices, and Accessories: Listed and labeled as defined in NFPA 70, Article 100, by a testing agency acceptable to authorities having jurisdiction, and marked for intended use.
- B. Comply with UL 467 for grounding and bonding materials and equipment.

PART 2 - PRODUCTS

2.1 CONDUCTORS

- A. Insulated Conductors: Copper wire or cable insulated for 600 V unless otherwise required by applicable Code or authorities having jurisdiction.
- B. Bare Copper Conductors:
  - 1. Solid Conductors: ASTM B 3.
  - 2. Stranded Conductors: ASTM B 8.
  - 3. Tinned Conductors: ASTM B 33.
  - 4. Bonding Cable: 28 kcmil, 14 strands of No. 17 AWG conductor, 1/4 inch (6 mm) in diameter.
  - 5. Bonding Conductor: No. 4 or No. 6 AWG, stranded conductor.
  - 6. Bonding Jumper: Copper tape, braided conductors, terminated with copper ferrules; 1-5/8 inches (41 mm) wide and 1/16 inch (1.6 mm) thick.
  - 7. Tinned Bonding Jumper: Tinned-copper tape, braided conductors, terminated with copper ferrules; 1-5/8 inches (41 mm) wide and 1/16 inch (1.6 mm) thick.
- C. Grounding Bus: Rectangular bars of annealed copper, 1/4 by 2 inches (6 by 50 mm) in cross section, unless otherwise indicated; with insulators.

## 2.2 CONNECTORS

- A. Listed and labeled by a nationally recognized testing laboratory acceptable to authorities having jurisdiction for applications in which used, and for specific types, sizes, and combinations of conductors and other items connected.
- B. Bolted Connectors for Conductors and Pipes: Copper or copper alloy, bolted pressure-type, with at least two bolts.
  - 1. Pipe Connectors: Clamp type, sized for pipe.
- C. Welded Connectors: Exothermic-welding kits of types recommended by kit manufacturer for materials being joined and installation conditions.

## PART 3 - EXECUTION

### 3.1 APPLICATIONS

- A. Conductors: Install stranded conductors, unless otherwise indicated.
- B. Conductor Terminations and Connections:
  - 1. Pipe and Equipment Grounding Conductor Terminations: Bolted connectors.
  - 2. Underground Connections: Welded connectors, except at test wells and as otherwise indicated.
  - 3. Connections to Ground Rods at Test Wells: Bolted connectors.
  - 4. Connections to Structural Steel: Welded connectors.

### 3.2 EQUIPMENT GROUNDING

- A. Install insulated equipment grounding conductors with all feeders and branch circuits.

### 3.3 INSTALLATION

- A. Grounding Conductors: Route along shortest and straightest paths possible, unless otherwise indicated or required by Code. Avoid obstructing access or placing conductors where they may be subjected to strain, impact, or damage.
- B. Bonding Straps and Jumpers: Install in locations accessible for inspection and maintenance, except where routed through short lengths of conduit.
  - 1. Bonding to Structure: Bond straps directly to basic structure, taking care not to penetrate any adjacent parts.
  - 2. Bonding to Equipment Mounted on Vibration Isolation Hangers and Supports: Install so vibration is not transmitted to rigidly mounted equipment.

3.4 FIELD QUALITY CONTROL

- A. Perform the following tests and inspections and prepare test reports:
  - 1. After installing grounding system but before permanent electrical circuits have been energized, test for compliance with requirements.
- B. Excessive Ground Resistance: If resistance to ground exceeds specified values, notify Engineer promptly and include recommendations to reduce ground resistance.

END OF SECTION 260526

SECTION 260529 - HANGERS AND SUPPORTS FOR ELECTRICAL SYSTEMS

PART 1 - GENERAL

1.1 RELATED DOCUMENTS

- A. Drawings and general provisions of the Contract, including General and Supplementary Conditions and Division 01 Specification Sections, apply to this Section.

1.2 SUMMARY

- A. This Section includes the following:
  - 1. Hangers and supports for electrical equipment and systems.
  - 2. Construction requirements for concrete bases.
- B. Related Sections include the following:
  - 1. Division 26 Section "Vibration And Seismic Controls For Electrical Systems" for products and installation requirements necessary for compliance with seismic criteria.

1.3 DEFINITIONS

- A. EMT: Electrical metallic tubing.
- B. IMC: Intermediate metal conduit.
- C. RMC: Rigid metal conduit.

1.4 PERFORMANCE REQUIREMENTS

- A. Design supports for multiple raceways capable of supporting combined weight of supported systems and its contents.
- B. Design equipment supports capable of supporting combined operating weight of supported equipment and connected systems and components.
- C. Rated Strength: Adequate in tension, shear, and pullout force to resist maximum loads calculated or imposed for this Project, with a minimum structural safety factor of five times the applied force.

1.5 QUALITY ASSURANCE

- A. Comply with NFPA 70.

PART 2 - PRODUCTS

2.1 SUPPORT, ANCHORAGE, AND ATTACHMENT COMPONENTS

- A. Steel Slotted Support Systems: Comply with MFMA-4, factory-fabricated components for field assembly.
  - 1. Manufacturers: Subject to compliance with requirements, provide products by one of the following:
    - a. Allied Tube & Conduit.
    - b. Cooper B-Line, Inc.; a division of Cooper Industries.
    - c. ERICO International Corporation.
    - d. GS Metals Corp.
    - e. Thomas & Betts Corporation.
    - f. Unistrut; Tyco International, Ltd.
    - g. Wesanco, Inc.
  - 2. Metallic Coatings: Hot-dip galvanized after fabrication and applied according to MFMA-4.
  - 3. Nonmetallic Coatings: Manufacturer's standard PVC, polyurethane, or polyester coating applied according to MFMA-4.
  - 4. Painted Coatings: Manufacturer's standard painted coating applied according to MFMA-4.
  - 5. Channel Dimensions: Selected for applicable load criteria.
- B. Raceway and Cable Supports: As described in NECA 1 and NECA 101.
- C. Conduit and Cable Support Devices: Steel hangers, clamps, and associated fittings, designed for types and sizes of raceway or cable to be supported.
- D. Support for Conductors in Vertical Conduit: Factory-fabricated assembly consisting of threaded body and insulating wedging plug or plugs for non-armored electrical conductors or cables in riser conduits. Plugs shall have number, size, and shape of conductor gripping pieces as required to suit individual conductors or cables supported. Body shall be malleable iron.
- E. Structural Steel for Fabricated Supports and Restraints: ASTM A 36/A 36M, steel plates, shapes, and bars; black and galvanized.
- F. Mounting, Anchoring, and Attachment Components: Items for fastening electrical items or their supports to building surfaces include the following:
  - 1. Powder-Actuated Fasteners: Threaded-steel stud, for use in hardened portland cement concrete, steel, or wood, with tension, shear, and pullout capacities appropriate for supported loads and building materials where used.
    - a. Manufacturers: Subject to compliance with requirements, provide products by one of the following:
      - 1) Hilti Inc.
      - 2) ITW Ramset/Red Head; a division of Illinois Tool Works, Inc.
      - 3) MKT Fastening, LLC.

- 4) Simpson Strong-Tie Co., Inc.; Masterset Fastening Systems Unit.
2. Mechanical-Expansion Anchors: Insert-wedge-type, zinc-coated steel, for use in hardened portland cement concrete with tension, shear, and pullout capacities appropriate for supported loads and building materials in which used.
  - a. Manufacturers: Subject to compliance with requirements, provide products by one of the following:
    - 1) Cooper B-Line, Inc.; a division of Cooper Industries.
    - 2) Empire Tool and Manufacturing Co., Inc.
    - 3) Hilti Inc.
    - 4) ITW Ramset/Red Head; a division of Illinois Tool Works, Inc.
    - 5) MKT Fastening, LLC.
3. Concrete Inserts: Steel or malleable-iron, slotted support system units similar to MSS Type 18; complying with MFMA-4 or MSS SP-58.
4. Clamps for Attachment to Steel Structural Elements: MSS SP-58, type suitable for attached structural element.
5. Through Bolts: Structural type, hex head, and high strength. Comply with ASTM A 325.
6. Toggle Bolts: All-steel springhead type.
7. Hanger Rods: Threaded steel.

## 2.2 FABRICATED METAL EQUIPMENT SUPPORT ASSEMBLIES

- A. Description: Welded or bolted, structural-steel shapes, shop or field fabricated to fit dimensions of supported equipment.
- B. Materials: Comply with requirements in Division 05 Section "Metal Fabrications" for steel shapes and plates.

## PART 3 - EXECUTION

### 3.1 APPLICATION

- A. Comply with NECA 1 and NECA 101 for application of hangers and supports for electrical equipment and systems except if requirements in this Section are stricter.
- B. Maximum Support Spacing and Minimum Hanger Rod Size for Raceway: Space supports for EMT, IMC, and RMC as scheduled in NECA 1, where its Table 1 lists maximum spacings less than stated in NFPA 70. Minimum rod size shall be **1/4 inch (6 mm)** in diameter.
- C. Multiple Raceways or Cables: Install trapeze-type supports fabricated with steel slotted support system, sized so capacity can be increased by at least 25 percent in future without exceeding specified design load limits.
  1. Secure raceways and cables to these supports with single-bolt conduit clamps.

- D. Spring-steel clamps designed for supporting single conduits without bolts may be used for **1-1/2-inch (38-mm)** and smaller raceways serving branch circuits and communication systems above suspended ceilings and for fastening raceways to trapeze supports.

### 3.2 SUPPORT INSTALLATION

- A. Comply with NECA 1 and NECA 101 for installation requirements except as specified in this Article.
- B. Raceway Support Methods: In addition to methods described in NECA 1, EMT, IMC, and RMC may be supported by openings through structure members, as permitted in NFPA 70.
- C. Strength of Support Assemblies: Where not indicated, select sizes of components so strength will be adequate to carry present and future static loads within specified loading limits. Minimum static design load used for strength determination shall be weight of supported components plus **200 lb (90 kg)**.
- D. Mounting and Anchorage of Surface-Mounted Equipment and Components: Anchor and fasten electrical items and their supports to building structural elements by the following methods unless otherwise indicated by code:
  - 1. To Wood: Fasten with lag screws or through bolts.
  - 2. To New Concrete: Bolt to concrete inserts.
  - 3. To Masonry: Approved toggle-type bolts on hollow masonry units and expansion anchor fasteners on solid masonry units.
  - 4. To Existing Concrete: Expansion anchor fasteners.
  - 5. Instead of expansion anchors, powder-actuated driven threaded studs provided with lock washers and nuts may be used in existing standard-weight concrete **4 inches (100 mm)** thick or greater. Do not use for anchorage to lightweight-aggregate concrete or for slabs less than **4 inches (100 mm)** thick.
  - 6. To Steel: Beam clamps (MSS Type 19, 21, 23, 25, or 27) complying with MSS SP-69.
  - 7. To Light Steel: Sheet metal screws.
  - 8. Items Mounted on Hollow Walls and Nonstructural Building Surfaces: Mount cabinets, panelboards, disconnect switches, control enclosures, pull and junction boxes, transformers, and other devices on slotted-channel racks attached to substrate by means that meet seismic-restraint strength and anchorage requirements.
- E. Drill holes for expansion anchors in concrete at locations and to depths that avoid reinforcing bars.

### 3.3 INSTALLATION OF FABRICATED METAL SUPPORTS

- A. Comply with installation requirements in Division 05 Section "Metal Fabrications" for site-fabricated metal supports.
- B. Cut, fit, and place miscellaneous metal supports accurately in location, alignment, and elevation to support and anchor electrical materials and equipment.
- C. Field Welding: Comply with AWS D1.1/D1.1M.

### 3.4 CONCRETE BASES

- A. Construct concrete bases of dimensions indicated but not less than **4 inches (100 mm)** larger in both directions than supported unit, and so anchors will be a minimum of 10 bolt diameters from edge of the base.
- B. Use **3000-psi (20.7-MPa)**, 28-day compressive-strength concrete. Concrete materials, reinforcement, and placement requirements are specified in Division 03 Section "Cast-in-Place Concrete."
- C. Anchor equipment to concrete base.
  - 1. Place and secure anchorage devices. Use supported equipment manufacturer's setting drawings, templates, diagrams, instructions, and directions furnished with items to be embedded.
  - 2. Install anchor bolts to elevations required for proper attachment to supported equipment.
  - 3. Install anchor bolts according to anchor-bolt manufacturer's written instructions.

### 3.5 PAINTING

- A. Touchup: Clean field welds and abraded areas of shop paint. Paint exposed areas immediately after erecting hangers and supports. Use same materials as used for shop painting. Comply with SSPC-PA 1 requirements for touching up field-painted surfaces.
  - 1. Apply paint by brush or spray to provide minimum dry film thickness of **2.0 mils (0.05 mm)**.
- B. Touchup: Comply with requirements in Division 09 painting Sections for cleaning and touchup painting of field welds, bolted connections, and abraded areas of shop paint on miscellaneous metal.
- C. Galvanized Surfaces: Clean welds, bolted connections, and abraded areas and apply galvanizing-repair paint to comply with ASTM A 780.

END OF SECTION 260529

SECTION 260533 - RACEWAY AND BOXES FOR ELECTRICAL SYSTEMS

PART 1 - GENERAL

1.1 RELATED DOCUMENTS

- A. Drawings and general provisions of the Contract, including General and Supplementary Conditions and Division 01 Specification Sections, apply to this Section.

1.2 SUMMARY

- A. This Section includes raceways, fittings, boxes, enclosures, and cabinets for electrical wiring.

1.3 DEFINITIONS

- A. EMT: Electrical metallic tubing.
- B. FMC: Flexible metal conduit.
- C. IMC: Intermediate metal conduit.
- D. LFMC: Liquidtight flexible metal conduit.

1.4 QUALITY ASSURANCE

- A. Electrical Components, Devices, and Accessories: Listed and labeled as defined in NFPA 70, Article 100, by a testing agency acceptable to authorities having jurisdiction, and marked for intended use.
- B. Comply with NFPA 70.

PART 2 - PRODUCTS

2.1 METAL CONDUIT AND TUBING

- A. Manufacturers: Subject to compliance with requirements, provide products by one of the following:
  1. AFC Cable Systems, Inc.
  2. Alflex Inc.
  3. Allied Tube & Conduit; a Tyco International Ltd. Co.
  4. Anamet Electrical, Inc.; Anaconda Metal Hose.
  5. Electri-Flex Co.
  6. Manhattan/CDT/Cole-Flex.

7. Maverick Tube Corporation.
  8. O-Z Gedney; a unit of General Signal.
  9. Wheatland Tube Company.
- B. Rigid Steel Conduit: ANSI C80.1.
- C. IMC: ANSI C80.6.
- D. EMT: ANSI C80.3.
- E. FMC: Zinc-coated steel.
- F. LFMC: Flexible steel conduit with PVC jacket.
- G. Fittings for Conduit (Including all Types and Flexible and Liquidtight), EMT, and Cable: NEMA FB 1; listed for type and size raceway with which used, and for application and environment in which installed.
1. Conduit Fittings for Hazardous (Classified) Locations: Comply with UL 886.
  2. Fittings for EMT: Steel, set-screw or compression type.
  3. Coating for Fittings for PVC-Coated Conduit: Minimum thickness, 0.040 inch (1 mm), with overlapping sleeves protecting threaded joints.
- H. Joint Compound for Rigid Steel Conduit or IMC: Listed for use in cable connector assemblies, and compounded for use to lubricate and protect threaded raceway joints from corrosion and enhance their conductivity.

## 2.2 METAL WIREWAYS

- A. Manufacturers: Subject to compliance with requirements, provide products by one of the following:
1. Cooper B-Line, Inc.
  2. Hoffman.
  3. Square D; Schneider Electric.
- B. Description: Sheet metal sized and shaped as indicated, NEMA 250, Type 1 or 3R as required by location, unless otherwise indicated.
- C. Fittings and Accessories: Include couplings, offsets, elbows, expansion joints, adapters, hold-down straps, end caps, and other fittings to match and mate with wireways as required for complete system.
- D. Wireway Covers: Hinged type; gasketed for damp or wet locations.
- E. Finish: Manufacturer's standard enamel finish.

## 2.3 BOXES, ENCLOSURES, AND CABINETS

- A. Manufacturers: Subject to compliance with requirements, provide products by one of the following:
1. Cooper Crouse-Hinds; Div. of Cooper Industries, Inc.
  2. EGS/Appleton Electric.
  3. Erickson Electrical Equipment Company.
  4. Hoffman.
  5. Hubbell Incorporated; Killark Electric Manufacturing Co. Division.
  6. O-Z/Gedney; a unit of General Signal.
  7. RACO; a Hubbell Company.
  8. Robroy Industries, Inc.; Enclosure Division.
  9. Scott Fetzer Co.; Adalet Division.
  10. Spring City Electrical Manufacturing Company.
  11. Thomas & Betts Corporation.
  12. Walker Systems, Inc.; Wiremold Company (The).
  13. Woodhead, Daniel Company; Woodhead Industries, Inc. Subsidiary.
- B. Sheet Metal Outlet and Device Boxes: NEMA OS 1; minimum 4" x 4" square, unless otherwise indicated.
- C. Cast-Metal Outlet and Device Boxes: NEMA FB 1, aluminum, Type FD, with gasketed cover.
- D. Small Sheet Metal Pull and Junction Boxes: NEMA OS 1.
- E. Cast-Metal Access, Pull, and Junction Boxes: NEMA FB 1, cast aluminum with gasketed cover.
- F. Hinged-Cover Enclosures: NEMA 250, Type 1, with continuous-hinge cover with flush latch, unless otherwise indicated.
1. Metal Enclosures: Steel, finished inside and out with manufacturer's standard enamel.
- G. Cabinets:
1. NEMA 250, Type 1, galvanized-steel box with removable interior panel and removable front, finished inside and out with manufacturer's standard enamel.
  2. Hinged door in front cover with flush latch and concealed hinge.
  3. Key latch to match panelboards.
  4. Metal barriers to separate wiring of different systems and voltage.
  5. Accessory feet where required for freestanding equipment.

## PART 3 - EXECUTION

### 3.1 RACEWAY APPLICATION

- A. Comply with the following indoor applications, unless otherwise indicated:
1. Exposed, Not Subject to Physical Damage: EMT.

2. Exposed and Subject to Physical Damage: Rigid steel conduit. Includes raceways in the following locations:
    - a. Loading dock.
    - b. Corridors used for traffic of mechanized carts, forklifts, and pallet-handling units.
    - c. Mechanical rooms.
  3. Concealed in Ceilings and Interior Walls and Partitions: EMT.
  4. Connection to Vibrating Equipment (Including Transformers and Hydraulic, Pneumatic, Electric Solenoid, or Motor-Driven Equipment): FMC, except use LFMC in damp or wet locations.
  5. Damp or Wet Locations: Rigid steel conduit.
  6. Boxes and Enclosures: NEMA 250, Type 1, except use NEMA 250, Type 4, stainless steel in damp or wet locations.
- B. Minimum Raceway Size: 3/4-inch (21-mm) trade size.
- C. Raceway Fittings: Compatible with raceways and suitable for use and location.
1. Rigid and Intermediate Steel Conduit: Use threaded rigid steel conduit fittings, unless otherwise indicated.

### 3.2 INSTALLATION

- A. Comply with NECA 1 for installation requirements applicable to products specified in Part 2 except where requirements on Drawings or in this Article are stricter.
- B. Keep raceways at least 6 inches (150 mm) away from parallel runs of flues and steam or hot-water pipes. Install horizontal raceway runs above water and steam piping.
- C. Complete raceway installation before starting conductor installation.
- D. Support raceways as specified in Division 26 Section "Hangers and Supports for Electrical Systems."
- E. Arrange stub-ups so curved portions of bends are not visible above the finished slab.
- F. Install no more than the equivalent of three 90-degree bends in any conduit run except for communications conduits, for which fewer bends are allowed.
- G. Conceal conduit and EMT within finished walls, ceilings, and floors, unless otherwise indicated.
- H. Raceways Embedded in Slabs:
  1. Run conduit larger than 1-inch (27-mm) trade size, parallel or at right angles to main reinforcement. Where at right angles to reinforcement, place conduit close to slab support.
  2. Arrange raceways to cross building expansion joints at right angles with expansion fittings.
  3. Change to rigid steel conduit before rising above the floor.

- I. Threaded Conduit Joints, Exposed to Wet, Damp, Corrosive, or Outdoor Conditions: Apply listed compound to threads of raceway and fittings before making up joints. Follow compound manufacturer's written instructions.
- J. Raceway Terminations at Locations Subject to Moisture or Vibration: Use insulating bushings to protect conductors, including conductors smaller than No. 4 AWG.
- K. Install pull wires in empty raceways. Use polypropylene or monofilament plastic line with not less than **200-lb (90-kg)** tensile strength. Leave at least **12 inches (300 mm)** of slack at each end of pull wire.
- L. Install raceway sealing fittings at suitable, approved, and accessible locations and fill them with listed sealing compound. For concealed raceways, install each fitting in a flush steel box with a blank cover plate having a finish similar to that of adjacent plates or surfaces. Install raceway sealing fittings at the following points:
  - 1. Where conduits pass from warm to cold locations, such as boundaries of refrigerated spaces.
  - 2. Where otherwise required by NFPA 70.
- M. Flexible Conduit Connections: Use maximum of **72 inches (1830 mm)** of flexible conduit for equipment subject to vibration, noise transmission, or movement; and for transformers and motors.
  - 1. Use LFMC in damp or wet locations subject to severe physical damage.
- N. Recessed Boxes in Masonry Walls: Saw-cut opening for box in center of cell of masonry block, and install box flush with surface of wall.

### 3.3 FIRESTOPPING

- A. Apply firestopping to electrical penetrations of fire-rated floor and wall assemblies to restore original fire-resistance rating of assembly.

### 3.4 PROTECTION

- A. Provide final protection and maintain conditions that ensure coatings, finishes, and cabinets are without damage or deterioration at time of Substantial Completion.
  - 1. Repair damage to galvanized finishes with zinc-rich paint recommended by manufacturer.
  - 2. Repair damage to PVC or paint finishes with matching touchup coating recommended by manufacturer.

END OF SECTION 260533

SECTION 260548 - VIBRATION AND SEISMIC CONTROLS FOR ELECTRICAL SYSTEMS

PART 1 - GENERAL

1.1 RELATED DOCUMENTS

- A. Drawings and general provisions of the Contract, including General and Supplementary Conditions and Division 01 Specification Sections, apply to this Section.

1.2 SUMMARY

- A. This Section includes the following:
  - 1. Isolation pads.
  - 2. Spring isolators.
  - 3. Restrained spring isolators.
  - 4. Channel support systems.
  - 5. Restraint cables.
  - 6. Hanger rod stiffeners.
  - 7. Anchorage bushings and washers.
- B. Related Sections include the following:
  - 1. Division 26 Section "Hangers And Supports For Electrical Systems" for commonly used electrical supports and installation requirements.

1.3 DEFINITIONS

- A. The IBC: International Building Code.
- B. ICC-ES: ICC-Evaluation Service.
- C. OSHPD: Office of Statewide Health Planning and Development for the State of California.

1.4 PERFORMANCE REQUIREMENTS

- A. Seismic-Restraint Loading:
  - 1. Site Class as Defined in the IBC: as required by the Structural Engineer.
  - 2. Assigned Seismic Use Group or Building Category as Defined in the IBC: as required by the Structural Engineer.
    - a. Component Importance Factor: as required by the Structural Engineer.
    - b. Component Response Modification Factor: as required by the Structural Engineer
    - c. Component Amplification Factor: as required by the Structural Engineer.

3. Design Spectral Response Acceleration at Short Periods (0.2 Second): as required by the Structural Engineer.
4. Design Spectral Response Acceleration at 1.0-Second Period: as required by the Structural Engineer.

## 1.5 SUBMITTALS

### A. Product Data: For the following:

1. Include rated load, rated deflection, and overload capacity for each vibration isolation device.
2. Illustrate and indicate style, material, strength, fastening provision, and finish for each type and size of seismic-restraint component used.
  - a. Tabulate types and sizes of seismic restraints, complete with report numbers and rated strength in tension and shear as evaluated by an agency acceptable to authorities having jurisdiction.
  - b. Annotate to indicate application of each product submitted and compliance with requirements.
3. Restrained-Isolation Devices: Include ratings for horizontal, vertical, and combined loads.

### B. Delegated-Design Submittal: For vibration isolation and seismic-restraint details indicated to comply with performance requirements and design criteria, including analysis data signed and sealed by the qualified professional engineer responsible for their preparation.

1. Design Calculations: Calculate static and dynamic loading due to equipment weight and operation, seismic forces required to select vibration isolators and seismic restraints.
  - a. Coordinate design calculations with wind-load calculations required for equipment mounted outdoors. Comply with requirements in other Division 26 Sections for equipment mounted outdoors.
2. Indicate materials and dimensions and identify hardware, including attachment and anchorage devices.
3. Field-fabricated supports.
4. Seismic-Restraint Details:
  - a. Design Analysis: To support selection and arrangement of seismic restraints. Include calculations of combined tensile and shear loads.
  - b. Details: Indicate fabrication and arrangement. Detail attachments of restraints to the restrained items and to the structure. Show attachment locations, methods, and spacings. Identify components, list their strengths, and indicate directions and values of forces transmitted to the structure during seismic events. Indicate association with vibration isolation devices.
  - c. Preapproval and Evaluation Documentation: By an agency acceptable to authorities having jurisdiction, showing maximum ratings of restraint items and the basis for approval (tests or calculations).

- C. Coordination Drawings: Show coordination of seismic bracing for electrical components with other systems and equipment in the vicinity, including other supports and seismic restraints.
- D. Welding certificates.
- E. Field quality-control test reports.

#### 1.6 QUALITY ASSURANCE

- A. Comply with seismic-restraint requirements in the IBC unless requirements in this Section are more stringent.
- B. Structural Engineer Qualifications: Licensed in the same state as project.
- C. Seismic-restraint devices shall have horizontal and vertical load testing and analysis and shall bear anchorage preapproval OPA number from OSHPD, preapproval by ICC-ES, or preapproval by another agency acceptable to authorities having jurisdiction, showing maximum seismic-restraint ratings. Ratings based on independent testing are preferred to ratings based on calculations. If preapproved ratings are not available, submittals based on independent testing are preferred. Calculations (including combining shear and tensile loads) to support seismic-restraint designs must be signed and sealed by a qualified professional engineer.
- D. Comply with NFPA 70.

### PART 2 - PRODUCTS

#### 2.1 VIBRATION ISOLATORS

- A. Manufacturers: Subject to compliance with requirements, provide products by one of the following:
  - 1. Ace Mountings Co., Inc.
  - 2. Amber/Booth Company, Inc.
  - 3. California Dynamics Corporation.
  - 4. Isolation Technology, Inc.
  - 5. Kinetics Noise Control.
  - 6. Mason Industries.
  - 7. Vibration Eliminator Co., Inc.
  - 8. Vibration Isolation.
  - 9. Vibration Mountings & Controls, Inc.
- B. Pads: Arrange in single or multiple layers of sufficient stiffness for uniform loading over pad area, molded with a nonslip pattern and galvanized-steel baseplates, and factory cut to sizes that match requirements of supported equipment.
  - 1. Resilient Material: Oil- and water-resistant neoprene, rubber or hermetically sealed compressed fiberglass.
- C. Spring Isolators: Freestanding, laterally stable, open-spring isolators.

1. Outside Spring Diameter: Not less than 80 percent of the compressed height of the spring at rated load.
  2. Minimum Additional Travel: 50 percent of the required deflection at rated load.
  3. Lateral Stiffness: More than 80 percent of rated vertical stiffness.
  4. Overload Capacity: Support 200 percent of rated load, fully compressed, without deformation or failure.
  5. Baseplates: Factory drilled for bolting to structure and bonded to 1/4-inch- (6-mm-) thick, rubber isolator pad attached to baseplate underside. Baseplates shall limit floor load to 500 psig (3447 kPa).
  6. Top Plate and Adjustment Bolt: Threaded top plate with adjustment bolt and cap screw to fasten and level equipment.
- D. Restrained Spring Isolators: Freestanding, steel, open-spring isolators with seismic or limit-stop restraint.
1. Housing: Steel with resilient vertical-limit stops to prevent spring extension due to weight being removed; factory-drilled baseplate bonded to 1/4-inch- (6-mm-) thick, neoprene or rubber isolator pad attached to baseplate underside; and adjustable equipment mounting and leveling bolt that acts as blocking during installation.
  2. Restraint: Seismic or limit-stop as required for equipment and authorities having jurisdiction.
  3. Outside Spring Diameter: Not less than 80 percent of the compressed height of the spring at rated load.
  4. Minimum Additional Travel: 50 percent of the required deflection at rated load.
  5. Lateral Stiffness: More than 80 percent of rated vertical stiffness.
  6. Overload Capacity: Support 200 percent of rated load, fully compressed, without deformation or failure.

## 2.2 SEISMIC-RESTRAINT DEVICES

- A. Manufacturers: Subject to compliance with requirements, provide products by one of the following:
1. Amber/Booth Company, Inc.
  2. California Dynamics Corporation.
  3. Cooper B-Line, Inc.; a division of Cooper Industries.
  4. Hilti Inc.
  5. Loos & Co.; Seismic Earthquake Division.
  6. Mason Industries.
  7. TOLCO Incorporated; a brand of NIBCO INC.
  8. Unistrut; Tyco International, Ltd.
- B. General Requirements for Restraint Components: Rated strengths, features, and application requirements shall be as defined in reports by an agency acceptable to authorities having jurisdiction.
1. Structural Safety Factor: Allowable strength in tension, shear, and pullout force of components shall be at least four times the maximum seismic forces to which they will be subjected.

- C. Channel Support System: MFMA-3, shop- or field-fabricated support assembly made of slotted steel channels with accessories for attachment to braced component at one end and to building structure at the other end and other matching components and with corrosion-resistant coating; and rated in tension, compression, and torsion forces.
- D. Restraint Cables: ASTM A 603 galvanized-steel cables with end connections made of steel assemblies with thimbles, brackets, swivels, and bolts designed for restraining cable service; and with a minimum of two clamping bolts for cable engagement.
- E. Hanger Rod Stiffener: Steel tube or steel slotted-support-system sleeve with internally bolted connections to hanger rod. Do not weld stiffeners to rods.
- F. Bushings for Floor-Mounted Equipment Anchor: Neoprene bushings designed for rigid equipment mountings, and matched to type and size of anchors and studs.
- G. Bushing Assemblies for Wall-Mounted Equipment Anchorage: Assemblies of neoprene elements and steel sleeves designed for rigid equipment mountings, and matched to type and size of attachment devices.
- H. Resilient Isolation Washers and Bushings: One-piece, molded, oil- and water-resistant neoprene, with a flat washer face.
- I. Mechanical Anchor: Drilled-in and stud-wedge or female-wedge type in zinc-coated steel for interior applications and stainless steel for exterior applications. Select anchors with strength required for anchor and as tested according to ASTM E 488. Minimum length of eight times diameter.
- J. Adhesive Anchor: Drilled-in and capsule anchor system containing polyvinyl or urethane methacrylate-based resin and accelerator, or injected polymer or hybrid mortar adhesive. Provide anchor bolts and hardware with zinc-coated steel for interior applications and stainless steel for exterior applications. Select anchor bolts with strength required for anchor and as tested according to ASTM E 488.

### 2.3 FACTORY FINISHES

- A. Finish: Manufacturer's standard paint applied to factory-assembled and -tested equipment before shipping.
  - 1. Powder coating on springs and housings.
  - 2. All hardware shall be galvanized. Hot-dip galvanize metal components for exterior use.
  - 3. Baked enamel or powder coat for metal components on isolators for interior use.
  - 4. Color-code or otherwise mark vibration isolation and seismic-control devices to indicate capacity range.

### PART 3 - EXECUTION

#### 3.1 EXAMINATION

- A. Examine areas and equipment to receive vibration isolation and seismic-control devices for compliance with requirements for installation tolerances and other conditions affecting performance.
- B. Examine roughing-in of reinforcement and cast-in-place anchors to verify actual locations before installation.
- C. Proceed with installation only after unsatisfactory conditions have been corrected.

#### 3.2 APPLICATIONS

- A. Multiple Raceways or Cables: Secure raceways and cables to trapeze member with clamps approved for application by an agency acceptable to authorities having jurisdiction.
- B. Hanger Rod Stiffeners: Install hanger rod stiffeners where indicated or scheduled on Drawings to receive them and where required to prevent buckling of hanger rods due to seismic forces.
- C. Strength of Support and Seismic-Restraint Assemblies: Where not indicated, select sizes of components so strength will be adequate to carry present and future static and seismic loads within specified loading limits.

#### 3.3 SEISMIC-RESTRAINT DEVICE INSTALLATION

- A. Equipment and Hanger Restraints:
  - 1. Install restrained isolators on electrical equipment.
  - 2. Install resilient, bolt-isolation washers on equipment anchor bolts where clearance between anchor and adjacent surface exceeds 0.125 inch (3.2 mm).
  - 3. Install seismic-restraint devices using methods approved by an agency acceptable to authorities having jurisdiction providing required submittals for component.
- B. Install bushing assemblies for mounting bolts for wall-mounted equipment, arranged to provide resilient media where equipment or equipment-mounting channels are attached to wall.
- C. Attachment to Structure: If specific attachment is not indicated, anchor bracing to structure at flanges of beams, at upper truss chords of bar joists, or at concrete members.
- D. Drilled-in Anchors:
  - 1. Identify position of reinforcing steel and other embedded items prior to drilling holes for anchors. Do not damage existing reinforcing or embedded items during coring or drilling. Notify the structural engineer if reinforcing steel or other embedded items are encountered during drilling. Locate and avoid prestressed tendons, electrical and telecommunications conduit, and gas lines.

2. Do not drill holes in concrete or masonry until concrete, mortar, or grout has achieved full design strength.
3. Wedge Anchors: Protect threads from damage during anchor installation. Heavy-duty sleeve anchors shall be installed with sleeve fully engaged in the structural element to which anchor is to be fastened.
4. Adhesive Anchors: Clean holes to remove loose material and drilling dust prior to installation of adhesive. Place adhesive in holes proceeding from the bottom of the hole and progressing toward the surface in such a manner as to avoid introduction of air pockets in the adhesive.
5. Set anchors to manufacturer's recommended torque, using a torque wrench.
6. Install zinc-coated steel anchors for interior and stainless-steel anchors for exterior applications.

### 3.4 ACCOMMODATION OF DIFFERENTIAL SEISMIC MOTION

- A. Install flexible connections in runs of raceways, cables, wireways, cable trays, and busways where they cross seismic joints, where adjacent sections or branches are supported by different structural elements, and where they terminate with connection to equipment that is anchored to a different structural element from the one supporting them as they approach equipment.

### 3.5 ADJUSTING

- A. Adjust isolators after isolated equipment is at operating weight.
- B. Adjust limit stops on restrained spring isolators to mount equipment at normal operating height. After equipment installation is complete, adjust limit stops so they are out of contact during normal operation.
- C. Adjust active height of spring isolators.
- D. Adjust restraints to permit free movement of equipment within normal mode of operation.

END OF SECTION 260548

## SECTION 260553 - IDENTIFICATION FOR ELECTRICAL SYSTEMS

### PART 1 - GENERAL

#### 1.1 RELATED DOCUMENTS

- A. Drawings and general provisions of the Contract, including General and Supplementary Conditions and Division 01 Specification Sections, apply to this Section.

#### 1.2 SUMMARY

- A. This Section includes the following:
  - 1. Identification for raceway and metal-clad cable.
  - 2. Identification for conductors and communication and control cable.
  - 3. Warning labels and signs.
  - 4. Instruction signs.
  - 5. Equipment identification labels.
  - 6. Miscellaneous identification products.

#### 1.3 QUALITY ASSURANCE

- A. Comply with ANSI A13.1 and ANSI C2.
- B. Comply with NFPA 70.
- C. Comply with 29 CFR 1910.145.

#### 1.4 COORDINATION

- A. Coordinate identification names, abbreviations, colors, and other features with requirements in the Contract Documents, Shop Drawings, manufacturer's wiring diagrams, and the Operation and Maintenance Manual, and with those required by codes, standards, and 29 CFR 1910.145. Use consistent designations throughout Project.
- B. Coordinate installation of identifying devices with completion of covering and painting of surfaces where devices are to be applied.
- C. Coordinate installation of identifying devices with location of access panels and doors.
- D. Install identifying devices before installing acoustical ceilings and similar concealment.

PART 2 - PRODUCTS

2.1 RACEWAY IDENTIFICATION MATERIALS

- A. Comply with ANSI A13.1 for minimum size of letters for legend and for minimum length of color field for each raceway and cable size.
- B. Color for Printed Legend:
  - 1. Power Circuits: Black letters on an orange field.
  - 2. Legend: Indicate system or service and voltage, if applicable.
- C. Self-Adhesive Vinyl Labels: Preprinted, flexible label laminated with a clear, weather- and chemical-resistant coating and matching wraparound adhesive tape for securing ends of legend label.
- D. Snap-Around Labels: Slit, pretensioned, flexible, preprinted, color-coded acrylic sleeves, with diameter sized to suit diameter of raceway or cable it identifies and to stay in place by gripping action.
- E. Snap-Around, Color-Coding Bands: Slit, pretensioned, flexible, solid-colored acrylic sleeves, **2 inches (50 mm)** long, with diameter sized to suit diameter of raceway or cable it identifies and to stay in place by gripping action.
- F. Self-Adhesive Vinyl Tape: Colored, heavy duty, waterproof, fade resistant; **2 inches (50 mm)** wide; compounded for outdoor use.

2.2 CONDUCTOR AND COMMUNICATION- AND CONTROL-CABLE IDENTIFICATION MATERIALS

- A. Color-Coding Conductor Tape: Colored, self-adhesive vinyl tape not less than **3 mils (0.08 mm)** thick by **1 to 2 inches (25 to 50 mm)** wide.
- B. Marker Tapes: Vinyl or vinyl-cloth, self-adhesive wraparound type, with circuit identification legend machine printed by thermal transfer or equivalent process.
- C. Aluminum Wraparound Marker Labels: Cut from **0.014-inch- (0.35-mm-)** thick aluminum sheet, with stamped, embossed, or scribed legend, and fitted with tabs and matching slots for permanently securing around wire or cable jacket or around groups of conductors.
- D. Write-On Tags: Polyester tag, **0.010 inch (0.25 mm)** thick, with corrosion-resistant grommet and polyester or nylon tie for attachment to conductor or cable.
  - 1. Marker for Tags: Permanent, waterproof, black ink marker recommended by tag manufacturer.

2.3 WARNING LABELS AND SIGNS

- A. Comply with NFPA 70 and 29 CFR 1910.145.

- B. Self-Adhesive Warning Labels: Factory printed, multicolor, pressure-sensitive adhesive labels, configured for display on front cover, door, or other access to equipment, unless otherwise indicated.
- C. Baked-Enamel Warning Signs: Preprinted aluminum signs, punched or drilled for fasteners, with colors, legend, and size required for application. **1/4-inch (6.4-mm)** grommets in corners for mounting. Nominal size, **7 by 10 inches (180 by 250 mm)**.
- D. Metal-Backed, Butyrate Warning Signs: Weather-resistant, nonfading, preprinted, cellulose-acetate butyrate signs with **0.0396-inch (1-mm)** galvanized-steel backing; and with colors, legend, and size required for application. **1/4-inch (6.4-mm)** grommets in corners for mounting. Nominal size, **10 by 14 inches (250 by 360 mm)**.

## 2.4 INSTRUCTION SIGNS

- A. Engraved, laminated acrylic or melamine plastic, minimum **1/16 inch (1.6 mm)** thick for signs up to **20 sq. in. (129 sq. cm)** and **1/8 inch (3.2 mm)** thick for larger sizes.
  - 1. Engraved legend with black letters on white face.
  - 2. Punched or drilled for mechanical fasteners.
  - 3. Framed with mitered acrylic molding and arranged for attachment at applicable equipment.

## 2.5 EQUIPMENT IDENTIFICATION LABELS

- A. Engraved, Laminated Acrylic or Melamine Label: Punched or drilled for screw mounting. White letters on a dark-gray background. Minimum letter height shall be **3/8 inch (10 mm)**.
- B. Stenciled Legend: In nonfading, waterproof, black ink or paint. Minimum letter height shall be **1 inch (25 mm)**.

## 2.6 MISCELLANEOUS IDENTIFICATION PRODUCTS

- A. Cable Ties: Fungus-inert, self-extinguishing, 1-piece, self-locking, Type 6/6 nylon cable ties.
  - 1. Minimum Width: **3/16 inch (5 mm)**.
  - 2. Tensile Strength: **50 lb (22.6 kg)**, minimum.
  - 3. Temperature Range: **Minus 40 to plus 185 deg F (Minus 40 to plus 85 deg C)**.
  - 4. Color: Black, except where used for color-coding.
- B. Paint: Paint materials and application requirements are specified in Division 09 painting Sections.
- C. Fasteners for Labels and Signs: Self-tapping, stainless-steel screws or stainless-steel machine screws with nuts and flat and lock washers.

PART 3 - EXECUTION

3.1 APPLICATION

- A. Power-Circuit Conductor Identification: For primary and secondary conductors No. 1/0 AWG and larger in vaults, pull and junction boxes, manholes, and handholes use color-coding conductor tape. Identify source and circuit number of each set of conductors. For single conductor cables, identify phase in addition to the above.
- B. Branch-Circuit Conductor Identification: Where there are conductors for more than three branch circuits in same junction or pull box, use color-coding conductor tape. Identify each ungrounded conductor according to source and circuit number.
  - 1. Where existing phase conductors are being re-used as neutral conductors, provide white tape around the neutral conductor in each junction box, enclosure and termination.
- C. Conductors to Be Extended in the Future: Attach marker tape to conductors and list source and circuit number.
- D. Auxiliary Electrical Systems Conductor Identification: Identify field-installed alarm, control, signal, sound, intercommunications, voice, and data connections.
  - 1. Identify conductors, cables, and terminals in enclosures and at junctions, terminals, and pull points. Identify by system and circuit designation.
  - 2. Use system of marker tape designations that is uniform and consistent with system used by manufacturer for factory-installed connections.
  - 3. Coordinate identification with Project Drawings, manufacturer's wiring diagrams, and Operation and Maintenance Manual.
- E. Warning Labels for Indoor Cabinets, Boxes, and Enclosures for Power and Lighting: Comply with 29 CFR 1910.145 and apply self-adhesive warning labels. Identify system voltage with black letters on an orange background. Apply to exterior of door, cover, or other access.
  - 1. Equipment with Multiple Power or Control Sources: Apply to door or cover of equipment including, but not limited to, the following:
    - a. Power transfer switches.
    - b. Controls with external control power connections.
  - 2. Equipment Requiring Workspace Clearance According to NFPA 70: Unless otherwise indicated, apply to door or cover of equipment but not on flush panelboards and similar equipment in finished spaces.
  - 3. Existing Phase Conductors Being Used as Neutral Conductors: Provide warning sign at panelboard of origination and at each accessible junction box and terminal cabinet indicating that existing phase conductors are now being used as neutral conductors, and are identified with white tape.
- F. Instruction Signs:

1. Operating Instructions: Install instruction signs to facilitate proper operation and maintenance of electrical systems and items to which they connect. Install instruction signs with approved legend where instructions are needed for system or equipment operation.
  2. Emergency Operating Instructions: Install instruction signs with white legend on a red background with minimum **3/8-inch- (10-mm-)** high letters for emergency instructions at equipment used for power transfer.
- G. Equipment Identification Labels: On each unit of equipment, install unique designation label that is consistent with wiring diagrams, schedules, and Operation and Maintenance Manual. Apply labels to disconnect switches and protection equipment, central or master units, control panels, control stations, terminal cabinets, and racks of each system. Systems include power, lighting, control, communication, signal, monitoring, and alarm systems unless equipment is provided with its own identification.
1. Labeling Instructions:
    - a. Indoor Equipment: Engraved, laminated acrylic or melamine label. Unless otherwise indicated, provide a single line of text with **1/2-inch- (13-mm-)** high letters on **1-1/2-inch- (38-mm-)** high label; where 2 lines of text are required, use labels **2 inches (50 mm)** high.
    - b. Outdoor Equipment: Engraved, laminated acrylic or melamine label.
    - c. Elevated Components: Increase sizes of labels and letters to those appropriate for viewing from the floor.
  2. Equipment to Be Labeled:
    - a. Panelboards, electrical cabinets, and enclosures.
    - b. Access doors and panels for concealed electrical items.
    - c. Emergency system boxes and enclosures.
    - d. Disconnect switches.
    - e. Contactors.
    - f. Dimmer cabinets.
    - g. Remote-controlled switches, dimmer modules, and control devices.
    - h. Terminals junction boxes..

### 3.2 INSTALLATION

- A. Verify identity of each item before installing identification products.
- B. Location: Install identification materials and devices at locations for most convenient viewing without interference with operation and maintenance of equipment.
- C. Apply identification devices to surfaces that require finish after completing finish work.
- D. Self-Adhesive Identification Products: Clean surfaces before application, using materials and methods recommended by manufacturer of identification device.
- E. Attach nonadhesive signs and plastic labels with screws and auxiliary hardware appropriate to the location and substrate.

- F. System Identification Color Banding for Raceways and Cables: Each color band shall completely encircle cable or conduit. Place adjacent bands of two-color markings in contact, side by side. Locate bands at changes in direction, at penetrations of walls and floors, at **50-foot (15-m)** maximum intervals in straight runs, and at **25-foot (7.6-m)** maximum intervals in congested areas.
- G. Color-Coding for Phase and Voltage Level Identification, 600 V and Less: Use the colors listed below for ungrounded service, feeder, and branch-circuit conductors.
1. Color shall be factory applied or, for sizes larger than No. 10 AWG if authorities having jurisdiction permit, field applied.
  2. Colors for 208/120-V Circuits:
    - a. Phase A: Black.
    - b. Phase B: Red.
    - c. Phase C: Blue.
  3. Colors for 480/277-V Circuits:
    - a. Phase A: Brown.
    - b. Phase B: Orange.
    - c. Phase C: Yellow.
  4. Field-Applied, Color-Coding Conductor Tape: Apply in half-lapped turns for a minimum distance of **6 inches (150 mm)** from terminal points and in boxes where splices or taps are made. Apply last two turns of tape with no tension to prevent possible unwinding. Locate bands to avoid obscuring factory cable markings.
- H. Aluminum Wraparound Marker Labels and Metal Tags: Secure tight to surface of conductor or cable at a location with high visibility and accessibility.
- I. Painted Identification: Prepare surface and apply paint according to Division 09 painting Sections.

END OF SECTION 260553

SECTION 262416 - PANELBOARDS

PART 1 - GENERAL

1.1 RELATED DOCUMENTS

- A. Drawings and general provisions of the Contract, including General and Supplementary Conditions and Division 01 Specification Sections, apply to this Section.

1.2 SUMMARY

- A. Section Includes:
  - 1. Lighting and appliance branch-circuit panelboards.

1.3 PERFORMANCE REQUIREMENTS

- A. Seismic Performance: Panelboards shall withstand the effects of earthquake motions determined according to SEI/ASCE 7.
  - 1. The term "withstand" means "the unit will remain in place without separation of any parts from the device when subjected to the seismic forces specified and the unit will be fully operational after the seismic event."

1.4 SUBMITTALS

- A. Product Data: For each type of panelboard, switching and overcurrent protective device, transient voltage suppression device, accessory, and component indicated. Include dimensions and manufacturers' technical data on features, performance, electrical characteristics, ratings, and finishes.
- B. Shop Drawings: For each panelboard and related equipment.
  - 1. Include dimensioned plans, elevations, sections, and details. Show tabulations of installed devices, equipment features, and ratings.
  - 2. Detail enclosure types and details for types other than NEMA 250, Type 1.
  - 3. Detail bus configuration, current, and voltage ratings.
  - 4. Short-circuit current rating of panelboards and overcurrent protective devices.
  - 5. Include evidence of NRTL listing for series rating of installed devices.
  - 6. Detail features, characteristics, ratings, and factory settings of individual overcurrent protective devices and auxiliary components.
  - 7. Include wiring diagrams for power, signal, and control wiring.
  - 8. Include time-current coordination curves for each type and rating of overcurrent protective device included in panelboards. Submit on translucent log-log graft paper; include selectable ranges for each type of overcurrent protective device.

- C. Seismic Qualification Certificates: Submit certification that panelboards, overcurrent protective devices, accessories, and components will withstand seismic forces defined in Division 26 Section "Vibration and Seismic Controls for Electrical Systems." Include the following:
  - 1. Basis for Certification: Indicate whether withstand certification is based on actual test of assembled components or on calculation.
  - 2. Dimensioned Outline Drawings of Equipment Unit: Identify center of gravity and locate and describe mounting and anchorage provisions.
  - 3. Detailed description of equipment anchorage devices on which the certification is based and their installation requirements.
- D. Operation and Maintenance Data: For panelboards and components to include in emergency, operation, and maintenance manuals. In addition to items specified in Division 01 Section "Operation and Maintenance Data," include the following:
  - 1. Manufacturer's written instructions for testing and adjusting overcurrent protective devices.
  - 2. Time-current curves, including selectable ranges for each type of overcurrent protective device that allows adjustments.

#### 1.5 QUALITY ASSURANCE

- A. Source Limitations: Obtain panelboards, overcurrent protective devices, components, and accessories from single source from single manufacturer.
- B. Product Selection for Restricted Space: Drawings indicate maximum dimensions for panelboards including clearances between panelboards and adjacent surfaces and other items. Comply with indicated maximum dimensions.
- C. Electrical Components, Devices, and Accessories: Listed and labeled as defined in NFPA 70, by a qualified testing agency, and marked for intended location and application.
- D. Comply with NEMA PB 1.
- E. Comply with NFPA 70.

#### 1.6 DELIVERY, STORAGE, AND HANDLING

- A. Remove loose packing and flammable materials from inside panelboards; install temporary electric heating (250 W per panelboard) to prevent condensation.
- B. Handle and prepare panelboards for installation according to NEMA PB 1.

#### 1.7 PROJECT CONDITIONS

- A. Environmental Limitations:
  - 1. Do not deliver or install panelboards until spaces are enclosed and weathertight, wet work in spaces is complete and dry, work above panelboards is complete, and temporary

HVAC system is operating and maintaining ambient temperature and humidity conditions at occupancy levels during the remainder of the construction period.

2. Rate equipment for continuous operation under the following conditions unless otherwise indicated:
  - a. Ambient Temperature: Not exceeding **minus 22 deg F (minus 30 deg C)** to **plus 104 deg F (plus 40 deg C)**.
  - b. Altitude: Not exceeding **6600 feet (2000 m)**.

B. Service Conditions: NEMA PB 1, usual service conditions, as follows:

1. Ambient temperatures within limits specified.
2. Altitude not exceeding **6600 feet (2000 m)**.

C. Interruption of Existing Electric Service: Do not interrupt electric service to facilities occupied by Owner or others unless permitted under the following conditions and then only after arranging to provide temporary electric service according to requirements indicated:

1. Notify Architect/Owner no fewer than two weeks in advance of proposed interruption of electric service.
2. Do not proceed with interruption of electric service without Architect/Owner's written permission.
3. Comply with NFPA 70E.

## 1.8 COORDINATION

- A. Coordinate layout and installation of panelboards and components with other construction that penetrates walls or is supported by them, including electrical and other types of equipment, raceways, piping, encumbrances to workspace clearance requirements, and adjacent surfaces. Maintain required workspace clearances and required clearances for equipment access doors and panels.
- B. Coordinate sizes and locations of concrete bases with actual equipment provided. Cast anchor-bolt inserts into bases. Concrete, reinforcement, and formwork requirements are specified in Division 03.

## 1.9 EXTRA MATERIALS

- A. Furnish extra materials that match products installed and that are packaged with protective covering for storage and identified with labels describing contents.
  1. Keys: Two spares for each type of panelboard cabinet lock.
  2. Fuses for Fused Switches: Equal to 10 percent of quantity installed for each size and type, but no fewer than three of each size and type.

PART 2 - PRODUCTS

2.1 GENERAL REQUIREMENTS FOR PANELBOARDS

- A. Fabricate and test panelboards according to IEEE 344 to withstand seismic forces defined in Division 26 Section "Vibration and Seismic Controls for Electrical Systems."
- B. Enclosures: Flush- and surface-mounted cabinets.
  - 1. Rated for environmental conditions at installed location.
    - a. Indoor Dry and Clean Locations: NEMA 250, Type 1.
    - b. Outdoor Locations: NEMA 250, Type 3R.
  - 2. Hinged Front Cover: Entire front trim hinged to box and with standard door within hinged trim cover.
  - 3. Directory Card: Inside panelboard door, mounted in transparent card holder.
- C. Incoming Mains Location: Top and bottom.
- D. Phase, Neutral, and Ground Buses:
  - 1. Material: Tin-plated aluminum or hard-drawn copper, 98 percent conductivity.
  - 2. Equipment Ground Bus: Adequate for feeder and branch-circuit equipment grounding conductors; bonded to box.
  - 3. Isolated Ground Bus: Adequate for branch-circuit isolated ground conductors; insulated from box.
  - 4. Extra-Capacity Neutral Bus: Neutral bus rated 200 percent of phase bus and UL listed as suitable for nonlinear loads.
- E. Conductor Connectors: Suitable for use with conductor material and sizes.
  - 1. Material: Hard-drawn copper, 98 percent conductivity.
  - 2. Lugs: Mechanical type.
  - 3. Extra-Capacity Neutral Lugs: Rated 200 percent of phase lugs mounted on extra-capacity neutral bus.
- F. Future Devices: Mounting brackets, bus connections, filler plates, and necessary appurtenances required for future installation of devices.
- G. Panelboard Short-Circuit Current Rating: Rated for series-connected system with integral or remote upstream overcurrent protective devices and labeled by an NRTL. Include size and type of allowable upstream and branch devices, listed and labeled for series-connected short-circuit rating by an NRTL.

2.2 LIGHTING AND APPLIANCE BRANCH-CIRCUIT PANELBOARDS

- A. Manufacturers: Subject to compliance with requirements, provide products by one of the following:

1. Eaton Electrical Inc.; Cutler-Hammer Business Unit.
  2. General Electric Company; GE Consumer & Industrial - Electrical Distribution.
  3. Siemens Energy & Automation, Inc.
  4. Square D; a brand of Schneider Electric.
- B. Panelboards: NEMA PB 1, lighting and appliance branch-circuit type.
- C. Branch Overcurrent Protective Devices: Bolt-on circuit breakers, replaceable without disturbing adjacent units.
- D. Doors: Concealed hinges; secured with flush latch with tumbler lock; keyed alike.

### 2.3 DISCONNECTING AND OVERCURRENT PROTECTIVE DEVICES

- A. Manufacturers: Subject to compliance with requirements, provide products by one of the following:
1. Eaton Electrical Inc.; Cutler-Hammer Business Unit.
  2. General Electric Company; GE Consumer & Industrial - Electrical Distribution.
  3. Siemens Energy & Automation, Inc.
  4. Square D; a brand of Schneider Electric.
- B. Molded-Case Circuit Breaker (MCCB): Comply with UL 489, with interrupting capacity to meet available fault currents.
1. Thermal-Magnetic Circuit Breakers: Inverse time-current element for low-level overloads, and instantaneous magnetic trip element for short circuits. Adjustable magnetic trip setting for circuit-breaker frame sizes 250 A and larger.
  2. Adjustable Instantaneous-Trip Circuit Breakers: Magnetic trip element with front-mounted, field-adjustable trip setting.
  3. Electronic trip circuit breakers with rms sensing; field-replaceable rating plug or field-replicable electronic trip; and the following field-adjustable settings:
    - a. Instantaneous trip.
    - b. Long- and short-time pickup levels.
    - c. Long- and short-time time adjustments.
    - d. Ground-fault pickup level, time delay, and  $I^2t$  response.
  4. GFCI Circuit Breakers: Single- and two-pole configurations with Class A ground-fault protection (6-mA trip).
  5. Ground-Fault Equipment Protection (GFEP) Circuit Breakers: Class B ground-fault protection (30-mA trip).
  6. Molded-Case Circuit-Breaker (MCCB) Features and Accessories:
    - a. Standard frame sizes, trip ratings, and number of poles.
    - b. Lugs: Mechanical style, suitable for number, size, trip ratings, and conductor materials.
    - c. Application Listing: Appropriate for application; Type SWD for switching fluorescent lighting loads; Type HID for feeding fluorescent and high-intensity discharge (HID) lighting circuits.

- d. Multipole units enclosed in a single housing or factory assembled to operate as a single unit.
  - e. Handle Clamp: Loose attachment, for holding circuit-breaker handle in on position.
- C. Fused Switch: NEMA KS 1, Type HD; clips to accommodate specified fuses; lockable handle.
- 1. Fuses, and Spare-Fuse Cabinet: Comply with requirements specified in Division 26 Section "Fuses."
  - 2. Fused Switch Features and Accessories: Standard ampere ratings and number of poles.
  - 3. Auxiliary Contacts: One normally open and normally closed contact(s) that operate with switch handle operation.

### PART 3 - EXECUTION

#### 3.1 EXAMINATION

- A. Receive, inspect, handle, and store panelboards according to NEMA PB 1.1.
- B. Examine panelboards before installation. Reject panelboards that are damaged or rusted or have been subjected to water saturation.
- C. Examine elements and surfaces to receive panelboards for compliance with installation tolerances and other conditions affecting performance of the Work.
- D. Proceed with installation only after unsatisfactory conditions have been corrected.

#### 3.2 INSTALLATION

- A. Install panelboards and accessories according to NEMA PB 1.1.
- B. Equipment Mounting: Install floor-mounted panelboards on concrete bases, **4-inch (100-mm)** nominal thickness. Comply with requirements for concrete base specified in Division 03 Section "Cast-in-Place Concrete."
  - 1. Install dowel rods to connect concrete base to concrete floor. Unless otherwise indicated, install dowel rods on **18-inch (450-mm)** centers around full perimeter of base.
  - 2. For panelboards, install epoxy-coated anchor bolts that extend through concrete base and anchor into structural concrete floor.
  - 3. Place and secure anchorage devices. Use setting drawings, templates, diagrams, instructions, and directions furnished with items to be embedded.
  - 4. Install anchor bolts to elevations required for proper attachment to panelboards.
  - 5. Attach panelboard to the vertical finished or structural surface behind the panelboard.
- C. Temporary Lifting Provisions: Remove temporary lifting eyes, channels, and brackets and temporary blocking of moving parts from panelboards.
- D. Comply with mounting and anchoring requirements specified in Division 26 Section "Vibration and Seismic Controls for Electrical Systems."

- E. Mount wall-mounted panelboards with top of trim **78 inches (1950 mm)** above finished floor unless otherwise indicated.
- F. Mount panelboard cabinet plumb and rigid without distortion of box. Mount recessed panelboards with fronts uniformly flush with wall finish and mating with back box.
- G. Install overcurrent protective devices and controllers not already factory installed.
  - 1. Set field-adjustable, circuit-breaker trip ranges.
- H. Install filler plates in unused spaces.
- I. Stub four **1-inch (27-GRC)** empty conduits from panelboard into accessible ceiling space or space designated to be ceiling space in the future. Stub four **1-inch (27-GRC)** empty conduits into raised floor space or below slab not on grade.
- J. Arrange conductors in gutters into groups and bundle and wrap with wire ties.
- K. Comply with NECA 1.

### 3.3 IDENTIFICATION

- A. Identify field-installed conductors, interconnecting wiring, and components; provide warning signs complying with Division 26 Section "Identification for Electrical Systems."
- B. Create a directory to indicate installed circuit loads; incorporate Owner's final room designations. Obtain approval before installing. Use a computer or typewriter to create directory; handwritten directories are not acceptable.
- C. Panelboard Nameplates: Label each panelboard with a nameplate complying with requirements for identification specified in Division 26 Section "Identification for Electrical Systems."
- D. Device Nameplates: Label each branch circuit device in distribution panelboards with a nameplate complying with requirements for identification specified in Division 26 Section "Identification for Electrical Systems."

### 3.4 FIELD QUALITY CONTROL

- A. Perform tests and inspections.
- B. Acceptance Testing Preparation:
  - 1. Test insulation resistance for each panelboard bus, component, connecting supply, feeder, and control circuit.
  - 2. Test continuity of each circuit.
- C. Tests and Inspections:
  - 1. Perform each visual and mechanical inspection and electrical test stated in NETA Acceptance Testing Specification. Certify compliance with test parameters.

2. Correct malfunctioning units on-site, where possible, and retest to demonstrate compliance; otherwise, replace with new units and retest.
- D. Panelboards will be considered defective if they do not pass tests and inspections.
  - E. Prepare test and inspection reports, including a certified report that identifies panelboards included and that describes scanning results. Include notation of deficiencies detected, remedial action taken, and observations after remedial action.

### 3.5 ADJUSTING

- A. Adjust moving parts and operable component to function smoothly, and lubricate as recommended by manufacturer.
- B. Set field-adjustable circuit-breaker trip ranges as indicated

END OF SECTION 262416

SECTION 262726 - WIRING DEVICES

PART 1 - GENERAL

1.1 RELATED DOCUMENTS

- A. Drawings and general provisions of the Contract, including General and Supplementary Conditions and Division 01 Specification Sections, apply to this Section.

1.2 SUMMARY

- A. This Section includes the following:
  - 1. Receptacles, receptacles with integral GFCI, and associated device plates.
  - 2. Twist-locking receptacles.
  - 3. Snap switches and wall-box dimmers.
  - 4. Cord and plug sets.

1.3 SUBMITTALS

- A. Product Data: For each type of product indicated.
- B. Operation and Maintenance Data: For wiring devices to include in all manufacturers' packing label warnings and instruction manuals that include labeling conditions.

1.4 QUALITY ASSURANCE

- A. Source Limitations: Obtain each type of wiring device and associated wall plate through one source from a single manufacturer. Insofar as they are available, obtain all wiring devices and associated wall plates from a single manufacturer and one source.
- B. Electrical Components, Devices, and Accessories: Listed and labeled as defined in NFPA 70, Article 100, by a testing agency acceptable to authorities having jurisdiction, and marked for intended use.
- C. Comply with NFPA 70.

1.5 COORDINATION

- A. Receptacles for Owner-Furnished Equipment: Match plug configurations.
  - 1. Cord and Plug Sets: Match equipment requirements.

PART 2 - PRODUCTS

2.1 MANUFACTURERS

- A. Manufacturers' Names: Shortened versions (shown in parentheses) of the following manufacturers' names are used in other Part 2 articles:
1. Cooper Wiring Devices; a division of Cooper Industries, Inc. (Cooper).
  2. Hubbell Incorporated; Wiring Device-Kellems (Hubbell).
  3. Leviton Mfg. Company Inc. (Leviton).
  4. Pass & Seymour/Legrand; Wiring Devices & Accessories (Pass & Seymour).

2.2 STRAIGHT BLADE RECEPTACLES

- A. Convenience Receptacles, 125 V, 20 A: Comply with NEMA WD 1, NEMA WD 6 configuration 5-20R, and UL 498.
1. Products: Subject to compliance with requirements, provide one of the following:
    - a. Cooper; 5351 (single), 5352 (duplex).
    - b. Hubbell; HBL5351 (single), CR5352 (duplex).
    - c. Leviton; 5891 (single), 5352 (duplex).
    - d. Pass & Seymour; 5381 (single), 5352 (duplex).

2.3 TWIST-LOCKING RECEPTACLES

- A. Single Convenience Receptacles, 125 V, 20 A: Comply with NEMA WD 1, NEMA WD 6 configuration L5-20R, and UL 498.
1. Products: Subject to compliance with requirements, provide one of the following:
    - a. Cooper; L520R.
    - b. Hubbell; HBL2310.
    - c. Leviton; 2310.
    - d. Pass & Seymour; L520-R.
- B. Isolated-Ground, Single Convenience Receptacles, 125 V, 20 A:
1. Products: Subject to compliance with requirements, provide one of the following:
    - a. Hubbell; IG2310.
    - b. Leviton; 2310-IG.
  2. Description: Comply with NEMA WD 1, NEMA WD 6 configuration L5-20R, and UL 498. Equipment grounding contacts shall be connected only to the green grounding screw terminal of the device and with inherent electrical isolation from mounting strap. Isolation shall be integral to receptacle construction and not dependent on removable parts.

## 2.4 PENDANT CORD-CONNECTOR DEVICES

- A. Description: Matching, locking-type plug and receptacle body connector; NEMA WD 6 configurations L5-20P and L5-20R, heavy-duty grade.
1. Body: Nylon with screw-open cable-gripping jaws and provision for attaching external cable grip.
  2. External Cable Grip: Woven wire-mesh type made of high-strength galvanized-steel wire strand, matched to cable diameter, and with attachment provision designed for corresponding connector.

## 2.5 CORD AND PLUG SETS

- A. Description: Match voltage and current ratings and number of conductors to requirements of equipment being connected.
1. Cord: Rubber-insulated, stranded-copper conductors, with Type SOW-A jacket; with green-insulated grounding conductor and equipment-rating ampacity plus a minimum of 30 percent.
  2. Plug: Nylon body and integral cable-clamping jaws. Match cord and receptacle type for connection.

## 2.6 SNAP SWITCHES

- A. Comply with NEMA WD 1 and UL 20.
- B. Switches, 120/277 V, 20 A:
1. Products: Subject to compliance with requirements, provide one of the following:
    - a. Cooper; 2221 (single pole), 2222 (two pole), 2223 (three way), 2224 (four way).
    - b. Hubbell; CS1221 (single pole), CS1222 (two pole), CS1223 (three way), CS1224 (four way).
    - c. Leviton; 1221-2 (single pole), 1222-2 (two pole), 1223-2 (three way), 1224-2 (four way).
    - d. Pass & Seymour; 20AC1 (single pole), 20AC2 (two pole), 20AC3 (three way), 20AC4 (four way).
- C. Pilot Light Switches, 20 A:
1. Products: Subject to compliance with requirements, provide one of the following:
    - a. Cooper; 2221PL for 120 V and 277 V.
    - b. Hubbell; HPL1221PL for 120 V and 277 V.
    - c. Leviton; 1221-PLR for 120 V, 1221-7PLR for 277 V.
    - d. Pass & Seymour; PS20AC1-PLR for 120 V.
  2. Description: Single pole, with neon-lighted handle, illuminated when switch is "ON."
  3. K

## 2.7 WALL PLATES

- A. Single and combination types to match corresponding wiring devices.
  - 1. Plate-Securing Screws: Metal with head color to match plate finish.
  - 2. Material for Finished Spaces: Smooth, high-impact thermoplastic.
  - 3. Material for Unfinished Spaces: Galvanized steel.
  - 4. Material for Damp Locations: Cast aluminum with spring-loaded lift cover, and listed and labeled for use in "wet locations."
- B. Wet-Location, Weatherproof Cover Plates: NEMA 250, complying with type 3R weather-resistant, die-cast aluminum with lockable cover.

## 2.8 FINISHES

- A. Color: Wiring device catalog numbers in Section Text do not designate device color.
  - 1. Wiring Devices Connected to Normal Power System: As selected by Architect, unless otherwise indicated or required by NFPA 70 or device listing.
  - 2. Isolated-Ground Receptacles: As specified above, with orange triangle on face.

## PART 3 - EXECUTION

### 3.1 INSTALLATION

- A. Comply with NECA 1, including the mounting heights listed in that standard, unless otherwise noted.
- B. Coordination with Other Trades:
  - 1. Take steps to insure that devices and their boxes are protected. Do not place wall finish materials over device boxes and do not cut holes for boxes with routers that are guided by riding against outside of the boxes.
  - 2. Keep outlet boxes free of plaster, drywall joint compound, mortar, cement, concrete, dust, paint, and other material that may contaminate the raceway system, conductors, and cables.
  - 3. Install device boxes in brick or block walls so that the cover plate does not cross a joint unless the joint is troweled flush with the face of the wall.
  - 4. Install wiring devices after all wall preparation, including painting, is complete.
- C. Conductors:
  - 1. Do not strip insulation from conductors until just before they are spliced or terminated on devices.
  - 2. Strip insulation evenly around the conductor using tools designed for the purpose. Avoid scoring or nicking of solid wire or cutting strands from stranded wire.
  - 3. The length of free conductors at outlets for devices shall meet provisions of NFPA 70, Article 300, without pigtails.
  - 4. Existing Conductors:

- a. Cut back and pigtail, or replace all damaged conductors.
- b. Straighten conductors that remain and remove corrosion and foreign matter.
- c. Pigtailling existing conductors is permitted provided the outlet box is large enough.

D. Device Installation:

1. Replace all devices that have been in temporary use during construction or that show signs that they were installed before building finishing operations were complete.
2. Keep each wiring device in its package or otherwise protected until it is time to connect conductors.
3. Do not remove surface protection, such as plastic film and smudge covers, until the last possible moment.
4. Connect devices to branch circuits using pigtails that are not less than **6 inches (152 mm)** in length.
5. When there is a choice, use side wiring with binding-head screw terminals. Wrap solid conductor tightly clockwise, 2/3 to 3/4 of the way around terminal screw.
6. Use a torque screwdriver when a torque is recommended or required by the manufacturer.
7. When conductors larger than No. 12 AWG are installed on 15- or 20-A circuits, splice No. 12 AWG pigtails for device connections.
8. Tighten unused terminal screws on the device.
9. When mounting into metal boxes, remove the fiber or plastic washers used to hold device mounting screws in yokes, allowing metal-to-metal contact.

E. Receptacle Orientation:

1. Install ground pin of vertically mounted receptacles up, and on horizontally mounted receptacles to the right.

F. Device Plates: Do not use oversized or extra-deep plates. Repair wall finishes and remount outlet boxes when standard device plates do not fit flush or do not cover rough wall opening.

G. Arrangement of Devices: Unless otherwise indicated, mount flush, with long dimension vertical and with grounding terminal of receptacles on top. Group adjacent switches under single, multigang wall plates.

### 3.2 FIELD QUALITY CONTROL

A. Perform tests and inspections and prepare test reports.

1. Test Instruments: Use instruments that comply with UL 1436.
2. Test Instrument for Convenience Receptacles: Digital wiring analyzer with digital readout or illuminated LED indicators of measurement.

B. Tests for Convenience Receptacles:

1. Line Voltage: Acceptable range is 105 to 132 V.
2. Percent Voltage Drop under 15-A Load: A value of 6 percent or higher is not acceptable.
3. Ground Impedance: Values of up to 2 ohms are acceptable.
4. GFCI Trip: Test for tripping values specified in UL 1436 and UL 943.
5. Using the test plug, verify that the device and its outlet box are securely mounted.

6. The tests shall be diagnostic, indicating damaged conductors, high resistance at the circuit breaker, poor connections, inadequate fault current path, defective devices, or similar problems. Correct circuit conditions, remove malfunctioning units and replace with new ones, and retest as specified above.

END OF SECTION 262726

## SECTION 265561 - THEATRICAL LIGHTING & EQUIPMENT

### PART 1 - GENERAL

#### 1.0 COORDINATION

- A. This Specification Section and related Contract Drawings are prepared by Spectrum Professional Services, Inc. Questions regarding Theatrical Equipment should be addressed to them through the Architect.

#### 1.1 RELATED DOCUMENTS

- A. Drawings and general provisions of Contract, including General and Supplementary Conditions and Division 1 Specification Sections, apply to this Section.
- B. Drawings and requirements in Div. 11 "Theatrical Equipment" sections apply to and may affect the equipment specified in this section.

#### 1.2 SUMMARY

- A. This Section includes the following equipment for theatrical lighting systems:
  - a. Dimmers.
  - b. Dimmer Racks.
  - c. Theatrical Relay Systems.
  - d. Control System.
  - e. Connector Strips, GJB, Borderlight Cable, and Supports.
  - f. Plugging Boxes.

#### 1.3 PRIOR APPROVAL

- A. Only specific products and manufacturers are approved to provide equipment for this section.
- B. Submit request for approval, consisting of proposed bill of material, catalog data, proof of listing or recognition by an independent testing laboratory, and a written discussion outlining variations with this specification, as soon as possible, but in no case less than 10 working days prior to established bid date. Failure to follow these procedures shall be cause for denial of approval, and may lead to charging the costs of such action to the contractor.

#### 1.4 SUBMITTALS

- A. General: Submit 10 bound copies of the following in accordance with Conditions of Contract, Division 1 Specification Sections, as modified herein. Submit this within 25 working days of issuance of purchase order to manufacturer.
- B. The installer shall verify equipment is coordinated with other electrical and mechanical systems before passing the submittal drawings on for review. Verify final locations for rough-ins with field measurements and with the requirements of the actual equipment to be connected.
- C. Detail all interconnection between equipment, terminations and wire nomenclature. All distribution equipment shall be detailed to show circuit identification and outlet locations. All dimmer racks and control devices shall show mechanical sizes and layout of components as well as lug and terminal sizes. Internal wiring diagrams may be provided, but they shall not be the only way of determining system operation and performance, switch labels or written explanations shall be provided to

clearly describe control relationships for take control, panic, override and similar functions. All locks shall be identified as to key code.

- D. Custom devices as detailed in the contract documents and non catalog devices require complete detailed drawings to assure specification compliance and coordination with other systems.
- E. All control panels, dimmer racks, wiring racks and similar devices shall be labeled with engraved plastic identification tags or as required elsewhere in this specification.
- F. Clearly indicate weights, sizes, relevant seismic data and heat generated by each piece of equipment. Note special criteria related to placing equipment into place and installation. If any special environmental requirements exist, such as storage and operation temperatures and humidity, or ESD sensitivity, note these clearly on the submittal drawings. Also note fabrication time requirements for all devices with a manufacturing time greater than six weeks.
- G. The review of the first submittal and one resubmittal shall be deemed included in the contract. Any resubmittal shall be provided within 10 working days of return of the marked-up submittal by the electrical contractor to the vendor, or if time is particularly sensitive, from the posting by courier, of a marked up set of submittal drawings to the vendor by the Architect/ Engineer/ Consultant. Payment for the review of additional resubmittals shall be the responsibility of the installer and equipment manufacturer, until approval is secured.
- H. Product data for standard items: fixtures, lamps, distribution equipment, and control systems. Include dimensions and data on features and components. Include wiring diagrams, interconnection details and elevation views of front panels of control and indicating devices. Include illustrations and dimensioned outline drawings of fixtures. Include dimensioned drawings, identification details and data on ratings and features of distribution devices.
- I. Factory configuring data for connections, circuit and channel assignments, and field tests specified in Part 3 of this Section.

#### 1.5 MANUALS

- A. Submit 2 copies of owner's manual for approval to the Engineer within 10 working days after the equipment is accepted by the Architect/Engineer/Consultant.
- B. The following items are required to be included.
  - a. A clear statement of warranty, including starting and ending dates.
  - b. Final "as installed" revision of the drawings, with parts list and a set of catalog data.
  - c. Internal wiring diagrams that were not required as part of the submittal drawings, but were used to fabricate the system.
  - d. Operating manuals for the control systems.
  - e. Maintenance manuals for the dimmer racks and other items requiring regular service, including recommended spare parts.
  - f. A list of all software and the versions installed in the equipment. This may be noted within individual drawings or manuals.
  - g. The name, address, and telephone number of the person servicing the equipment, and the service manager for the manufacturer of all equipment provided.

- h. The name, address, and telephone number of the electrical contractor that installed the equipment.
- C. Provide 3 copies of the approved manuals to the owner within 10 working days after the receipt of one marked-up copy of the submitted manual by the manufacturer from the Consultant / Engineer.

1.6 QUALITY ASSURANCE

- A. Comply with NFPA 70 "National Electrical Code", UBC, and jurisdictional requirements for components and installation.
- B. Listing and Labeling: Provide only products that are listed and labeled by a Recognized Independent Testing Laboratory. Any subsequent or local testing that may be required shall be the responsibility of the manufacturer.
  - a. The terms "Listed" and "Labeled": As defined in the National Electrical Code, Article 100.
  - b. Equipment that may emit radio frequency interference shall comply with relevant FCC requirements Part 15 and Part 18 and be so labeled.
- C. Service Center: The manufacturer of the dimmers and lighting controls must maintain a service center capable of providing training, maintenance, parts, and emergency service and repairs at the project site with 24 hours maximum response time. The manufacturer shall maintain a 24 hour per day ,7 days per week, accessible telephone assistance service.
- D. Single Manufacturer: To assure coordinated performance the houselight and lobby light dimmer racks, dimmers, relay control system, demultiplexing / dimmer driver circuitry, houselight control system and worklight control system shall be of one manufacturer, who shall be responsible for coordinated operation as required herein. It is preferred, but not required, that all entertainment dimmers and the control console, and SMP be of the same manufacturer. This may be weighed as a factor in deciding the award of the contract.

1.7 WARRANTY

- A. All equipment shall be warranted to be free of defects in materials, workmanship and installation for the term of time shown below from the date of acceptance by the Architect / Engineer / Consultant.

| Device          | Warranty Term | Requirements  |
|-----------------|---------------|---|
| Dimmer modules  | 1 year        | On site or factory exchange/repair                                |
| Dimmer modules  | Second year   | Factory exchange/repair   |
| All software    | 5 years       | Provide debugged software, on site, does not include enhancements |
| All other items | 1 year        | On-site   |

- B. A warranty claim shall be deemed to be made when the fault is reported to the designated service contacts, not when the repair is made.

- C. On-site service shall be scheduled as is convenient for all parties, if the system is still operational,

and not endangering performances. If performances are jeopardized, then immediate action is expected, either service visit, no-charge loaner equipment or other action acceptable to the owner is required.

- D. Repairs made on a "factory exchange/repair" basis includes freight paid one way by each party, with a factory repair time of 10 working days, maximum.

## 1.8 EXTRA MATERIALS

- A. Furnish extra materials matching products installed, as described below, packaged with protective covering for storage, and identified with labels describing contents. Deliver extra materials to the owner and obtain a signed receipt.
  - a. Dimmer Modules: 1 of each type and rating installed.
  - b. Control Modules, DM and R, Provide 1 of each type installed.

## PART 2 - PRODUCTS

### 2.1 MANUFACTURERS

- A. Manufacturers: Subject to compliance with requirements, provide products by the following:

Entertainment Control Equipment and Dimmers:

- a. Leviton Colortran, Inc., Tualatin OR
- b. ETC Inc., Middleton, WI
- c. Strand Lighting Inc., Cypress, CA
- d. Entertainment Technologies Inc., Dallas, TX
  
- d. Distribution Equipment:
  - a. Leviton Colortran, Inc., Tualatin OR
  - b. ETC Inc., Middleton, WI
  - c. Strand Lighting Inc., Cypress, CA
  - d. Entertainment Technologies Inc., Dallas, TX
  - f. Union Connector Co., Inc., Roosevelt, NY
  - g. SECOA, Inc., Minneapolis, CA
  - h. Stagecraft Industries, Portland, OR

### 2.2 DISTRIBUTION COMPONENTS, GENERAL

- A. Metal Parts: Free from burrs and sharp corners and edges.
- B. Sheet Metal Components: Steel, formed and supported to prevent warping and sagging.
- C. Pigtaills: Factory wired, 3-wire extra hard usage rubber cord and plug connector assembly with approved cord strain relief device.
  - a. Length as shown on drawings or if not shown then as indicated below:
    - a. On devices above the stage -18 inches.
    - b. On devices above the house area - 3 feet.

- c. On plug boxes at the splay position - 5 feet.
- D. Single Plug Connectors: 2-pole, 3-wire, 20-ampere pin type, compliant with UL 498, unless noted otherwise.
- E. Multi Pin power connectors: Socapex 19 pin, 20 ampere rating type 419AR, solder connection only.
- F. Pipe for pipe battens: Schedule 40 black iron, 1 1/2" ID, painted flat black, unless indicated otherwise.
- G. Paint: All distribution equipment shall be painted flat black with a high temperature paint suitable for intended use without discoloring or peeling under application, unless noted on the drawings.
- H. Identification of Circuits: All distribution equipment shall be provided with 1.5" high circuit number identification labels. On connector strips and pigtail type boxes labels shall be engraved lamicoïd material fastened to wireway with rivets. In all cases label shall be in a black with white lettering stroke.. On floor pockets and other smaller devices, 1" lamicoïd labels shall be used. Colored and secured as herein.

## 2.3 DISTRIBUTION COMPONENTS

- A. Distribution Component Assemblies: NRTL listed and labeled.
- B. Connector Strip: Factory-wired wireway and receptacle assembly.
  - a. Lengths: As indicated.
  - b. Wireway: Sheet steel or extruded aluminum, with 3 x 4-1/2 inches nominal cross section dimensions and removable cover.
  - c. Receptacles: Flush mounted in wireway cover or pigtail mounted as shown on drawings. Wiring: Connect to terminal blocks with 125-deg C, cross-linked polyethylene insulated, identification labeled wire. Quantity and ratings as indicated.
  - d. Terminal Blocks: Molded-barrier type with screw lugs to suit supply conductors.
  - e. Mounting: double pipe bracket on 8' centers maximum. Upper pipe shall be by the rigging system, 30" strap brackets shall be provided to suspend the wireway below the upper pipe facilitating instrument storage. The lower pipe batten shall be provided by the stage lighting equipment manufacturer, and spaced for traditional c clamp access. All pipe battens shall be 1.5" ID schedule 40 black iron pipe, painted flat black, using internal splice sleeve, with center line marked with a yellow painted stripe.
  - f. Circuit Identification: Provide 2 1/2" high labels on both sides of the wireway at outlet locations. In addition, provide 1" high labels on pigtail connectors. Labels may be self adhesive panel markers (Brady, T&B, etc.), or painted legends, all in contrasting color for visibility from the floor.
- C. Plugging Boxes: Factory-wired wireway and receptacle assembly, 24-inches long except as otherwise indicated, and with the following features:
  - a. Wireway: Steel or extruded aluminum, with 3- by 4-1/2-inch nominal cross section and removable cover.
  - b. Receptacles: Flush mounted in wireway cover or pigtail mounted as shown on drawings. Wiring: Connect to terminal blocks with 125-deg C, cross-linked polyethylene insulated, identification labeled wire. Quantity and ratings as indicated.c.
  - c. Terminal Blocks: Molded barrier type with screw lugs to suit supply conductors.
  - d. Mounting: Surface or pipe as indicated.
- D. Feeder System for Hanging Devices: Feed each connector strip, continuous borderlight, and

hanging plugging box (drop box) with multiconductor cable as indicated. Cable shall be rubber covered type SO, supported at the gridiron junction box end with expanded net type strain relief device, at an intermediate point with a theatrical cable cradle, and on the batten end with compression type cable clamp fastened to batten. Provide sufficient cable length to allow lowering of the device to 2 feet above the stage floor. Where existing devices are removed, provide replacement units using the same number of borderlight cables, feeders, and wiring homeruns. Existing cable cradles, rigging attachments, conduits, bushings, etc. may be reused unless found to be in unacceptable condition in the opinion of the owner's representative (except borderlight cable must be all new SO cable.)

- E. Wall Pockets: Flush-mounted, receptacle outlet assembly with rating and quantity of receptacles as indicated. Provide 1" high circuit identification legends adjacent to each outlet.
  - a. Box: Steel, minimum of 16-gage by 4-inches deep.
  - b. Cover Plate: Provide steel plate, surface or flush mounted as required, securely mounting all outlets and labels. Cover shall be painted flat black or as noted by Architect.

## 2.9 DIMMER AND EQUIPMENT RACKS - "DM"

- A. General: Equipment enclosures shall be freestanding, of substantial welded metal framing with panels held in place with rustproof screws or bolts. All conduit entry panels in the top, sides, back and bottom shall be removable for punching, and firmly reinstalled using factory provided fasteners. All metal surfaces shall be properly cleaned, primed and painted in accordance with NEMA standards. Factory standard color shall be provided. All frames, panels, doors and otherwise externally accessible parts shall be connected to earth thru the system equipment ground path.
- B. Lugs and Bus Bars: Electrical bus bars shall be copper, with input lugs provided by the equipment manufacturer, sized for the feeder conductors. Provide full sized neutral and ground bars, with 96 tubular terminations for neutral wires and 48 tubular terminations for ground conductors, per dimmer rack section. Provide all required rack section interconnection buss bars and lugs for single feeders as required.
- C. Fault Current Rating: Dimmers with enclosure shall be sized and braced for 42,000 ampere short circuit current rating, and be so labeled. If input fuses are required to obtain this rating, provide 1 duplicate set of fuses as spares and show fusing computations on drawings.
- D. System Cooling: If dimmer system uses forced air ventilation to maintain operating temperature, system shall have an indication at the control booth and at the stage managers panel of any overtemperature condition, should it occur. Fans should only be on if required by temperature or instructed by control signals. If fans require maintenance, this must be plainly explained in the maintenance manuals. If dimmer system has filters in the air path, then an air flow detector shall be employed to warn the operator of reduced airflow, in a manner similar to the overtemp warning. System shall be capable of operating properly, at full load in ambient temperatures up to and including 40 degrees Celsius. Air input shall be a minimum of 6" above the floor. The installer shall provide a platform for the dimmer rack if required to comply with the air input distance requirements. Provide fan noise suppression device .
- E. Access: Front access shall be required for installation and maintenance of the equipment racks. Dimmer rack shall be provided with a locking door over all dimmer slots.
- F. Vibration Control: Provide vibration isolation pads, 4 per rack section, ribbed or waffle neoprene at least 1/2" thick and sized for loading of 50 to 75 psi.
- G. Wiring: All factory wiring shall be neatly dressed and labeled. All contractor connections shall be by labeled tubular terminal blocks. Contractor wiring shall be neatly dressed and labeled, and shall

not impede the airflow of the system.

- H. Dimmer Connections: Connections to and from the dimmer chassis shall be by connectors with integral pressure devices. Spring tension devices are preferred, but split brass pins are acceptable if the pins are accessible for spreading to restore tension. Control pins or connector shall break first upon removal, and make last upon insertion, to assure power connection pins do not arc if removed under load. Ground pin shall make first and break last for safety. Dimmer connectors shall not be damaged by placing the dimmer chassis on the floor, pins down. Chassis to dimmer rack mechanical alignment shall not be a function of the connector pins.
- I. Control Circuitry: Dimmer Rack shall operate from 2 simultaneous digital input signals, in a logical partition manner. Digital signal shall be USITT standard DMX and / or Ethernet based equivalent. Digital control circuitry located within the dimmer rack shall be isolated from the power sections of the enclosure by a physical barrier. The control circuitry shall be separate for each section of dimmers. Failure of one section shall not cause the other sections to fail. Dimmers shall be updated by the control circuitry at a rate of 30Hz, minimum.
- J. Back-Up Cues: Control circuitry shall have memory for 99 backup cues. These cues shall be programmed from a local keyboard or any of the DMX input signals, and recorded, along with fade times and preset identification from a handheld terminal device, with plug--in receptacles as shown on the drawings. The recall of the first 8 of these shall be from stage preset recall stations located as shown on the drawings. Playback access for these backup cues shall be only possible if no valid DMX signal is present on any signal input. Additional memory shall hold the output to all dimmers at the last valid level, in the event of control disruption, for at least 15 minutes, subject to the take control circuitry.
  - a. Houselight and worklight signals shall not be recorded into backup cues.
- K. Multiple Signal Inputs: For each partition, digital control circuitry shall have automatic priority switching (presence of a valid signal on a higher numbered port will take control from an operating lower numbered port) for at least 3 digital input ports, all capable of receiving USITT standard DMX-512 control signals. Electrical isolation of 2500 volts minimum shall be provided between the dimmer electronics and the data line. Voltage shall not be present on pins 4 & 5 of the XLR connectors. The dimmer manufacturer shall be responsible for all control signal compatibility.
- L. Rack Layout: Slot mapping or dimmer arrangement may be a software or hardware feature, with rack starting address a hardware function. A dimmer schedule and module diagram shall be provided on the face of the enclosure to locate dimmers in the system. Individual dimmer chassis or individual slots need not be labeled.
- M. All relays used in the system for control or power switching, except for control devices associated with the emergency transfer section, shall be mechanically held or otherwise immune to status changes upon power outages. All relays or contactors used for nondim or switching of power circuits shall be mechanically held and tungsten rated. All relays 15 amperes or less rating shall be plug in. Circuit breakers feeding such devices shall be UL listed for branch circuit protection.
- N. Modularity: Dimmers and control modules shall plug-in to the equipment racks in a positive manner. Dimmer chassis shall not require bolts or fasteners to be properly seated in the slots.
- O. Dimmers, General:
  - a. Dimmers shall be provided for line voltage incandescent loads.
  - b. These dimmers shall vary the output to the load in a stepless, continuous manner, tracking changes in the control signal in less than 25 milliseconds, without searching, instability, or any effect of hysteresis, and repeatable within .1 volt.

- c. Dimmers shall compensate for changes in the incoming line within available voltage. Changes of +/- 10 volts between 120 and 90 volts in the incoming line shall result in changes in the output of .1 volt maximum, within 40 milliseconds, integrated over 200 milliseconds.
  - d. Dimmers shall have a main circuit breaker, capable of removing the dimmer from the circuit and acting as the branch circuit protector. Circuit breakers shall maintain their standards approval even if thermally recalibrated for the application.
  - e. Optical isolation rated at 2500 volts minimum shall be provided between the power section of the dimmer and the control section of the dimmer.
  - f. Dimmer shall utilize SCR devices as the power switching devices. These SCRs shall be arranged in an inverse parallel configuration to provide switching for both halves of the sine wave. Output shall be essentially AC with less than .5 volt DC component. These SCR devices shall be a mechanically removable device, using regular tools, without soldering. The SCR shall have peak voltage rating of 700 volts and be rated for continuous load operation of twice the dimmer rating. SCR assemblies shall be thermally connected to the heatsink with a thermal compound to assure heat transfer and dissipation. Replacement SCR assemblies shall be available from specialized electronic parts distribution sources, in addition to the dimmer manufacturer.
  - g. Dimmer shall be provided with an inductor to limit objectionable interference with other electrical devices connected to the line or in the proximity of the equipment, and to reduce the audible noise in the lamps connected to the dimmer. The effectiveness of this filtering shall be measured as risetime, at the switchpoint. Provide plots or photographs from an oscilloscope of the output waveform as a part of the submittal package.
    - 1. The filtering of dimmer modules for stagelighting circuits shall exceed 400 microseconds, as measured with 80% load, 90 degree conduction angle, and 10 to 90% of the waveform.
    - 2. The filtering of dimmer modules for houselighting circuits shall exceed 800 microseconds, as measured with 80% load, 90 degree conduction angle, and 10 to 90% of the waveform.
  - h. Dimmer chassis shall have individual overtemperature protection, either by thermal elements within the circuit breaker, or other device within the chassis.
  - i. Dimmers shall be free of flashing and interaction with each other or line induced transients.
  - j. Dimmer chassis shall be provided with a non-dim selector switch to designate a dimmer as a switching only circuit. This function may alternatively be accomplished by functions at the control console. If neither of these is possible, then provide 5% spare dimmer chassis equipped for nondim operation.
  - k. Certain loads are to be controlled by relays, and others shall be controlled by relays and dimmers. Such controls shall be by the dimming equipment manufacturer, using GE RR-9 relays or acceptable alternative. Equipment shall be integral to dimming racks associated with the loads controlled.
- P. Acceptable Products: These dimmers and systems are acceptable, subject to the specifications:
- a. "DM":
    - a. Leviton Colortran, Inc., i Series

- b. ETC, Inc., Sensor – BASE BID FOR ALL SUPPLIERS
- c. Strand Lighting Inc., C21
- d. ET, Capio,

## 2.14 HOUSELIGHT CONTROLS

GENERAL: Intention to replace all existing control devices with new hardware (relays, switches, control devices, cue light, etc.) without changing either adding or deleting control capability.

- A. Provide houselight, and worklight controls as shown on the drawings. All sliders shall be 45 mm travel, scaled in 0 to 10 in whole and half "point" markings. All pushbuttons unless designated otherwise shall have longlife LED indicators of the status of their associated devices. Master controllers and remote master controllers shall have current drivers to assure linear control of the associated channel sliders. All pushbuttons shall have integrally captive keycaps, or be secured against keycap removal in an approved manner. Box and cover shall be grounded per manufacturer's written directions, and free of sensitivity to EDS per IEC 801-2 standard and withstand a 15Kv ESD without affecting operation of the control electronics.
- C. Dimmer control system shall have real-time supervisory memory that will monitor the control data to the dimmers, and hold the last valid state until new valid data is received or until programmable hold time has elapsed, and a programmable fade out is initiated. Programmable functions of this hold memory shall be accessible by the operator.
- D. See the drawings for the details of each control and control location. Each control panel shall be made of aluminum anodized in a color approved by the architect with labels as required, engraved or silkscreened in an approved contrasting color.
- E. Installers should note that the requirements of each of the manufacturers may vary from the conductors called out on the plans. Actual requirements will be as detailed on the successful manufacturer's submittal drawings.
- F. Entry Station: Pushbutton activates and deactivates indicating light and a preset scene of the houselight control system, as noted on the drawings. Stations shall be flush wall mounted, except as otherwise indicated. Stations plate shall be manufacturers standard, secured with a minimum of two screws to the box/conduit support system. Box and cover shall be grounded per manufacturer's written directions. Stations in the auditorium shall have keyed hinged cover. Control commands from entry stations and from either performance location shall be on a A last takes precedence technique from any station, and shall not permit locking type commands.
- G. Control Receptacle Stations: All portable control devices, consoles, handheld devices, etc. shall plug-in to receptacle stations as indicated. Receptacle stations shall be stainless steel, secured with a minimum of two screws to the box/conduit support system. Stations connected to digital signals shall have signal termination circuitry to automatically properly manage high speed bi-directional digital signals, with or without devices plugged into the stations. Connectors shall be metal, professional multi-pin "xlr" type connectors, with pressure type contacts. Outlets shall be labeled as to function in an approved manner. Stations shall be flush wall mounted, except as otherwise indicated. Box and cover shall be grounded per manufacturer's written directions.
- H. Digital Signal Distribution: Provide signal amplification/distribution equipment as shown on the drawings. Devices shall be rated for the signal and speed they are intended to process. Devices shall be bidirectional. Connect signals to the device in a manner that is consistent with the application, and that does not reduce the signal integrity. Devices shall be of the type shown, signal distribution hubs and/or digital signal combiner, with programmable starting address. Dimmer Digital Switch shall be powered Ethernet switch 3Com # 4400 PWR 24.

- I. Acceptable Products: This equipment is acceptable, subject to the specifications:
  - a. "Control Receptical Stations":
    - a. Leviton Colortran, Inc.
    - b. ETC, Inc.
    - c. Strand Lighting Inc.
    - d. Genlyte Controls
    - e. Pathway
  - b. "Digital Signal Distribution":
    - a. Leviton Colortran, Inc.
    - b. ETC, Inc.
    - c. Strand Lighting Inc.
    - d. Genlyte Controls
    - e. Pathway

#### 2.14 THEATRICAL RELAY SYSTEM

- A. Expandability: System shall be capable of increasing the number of control functions in the future by 25 percent of current capacity; to include equipment ratings, housing capacities, spare relays, terminals, number of conductors in control cables, and control software.
- B. Performance Requirements: Manual switch operation sends a digital signal to programmable-system control module that processes the signal according to its programming and routes an open or close command to one or more relays in the power-supply circuits to groups of lighting fixtures or other loads.
- C. Control Module Description: Comply with UL 508 (CSA C22.2, No. 14); microprocessor-based, programmable, control unit; mounted in preassembled, modular relay panel. Low-voltage-controlled, latching-type, single-pole lighting circuit relays shall be prime output circuit devices. Where indicated, a limited number of digital or analog, low-voltage control-circuit outputs shall be supported by control unit and circuit boards associated with relays. Control units shall be capable of receiving inputs from sensors and other sources. Line-voltage components and wiring shall be separated from low-voltage components and wiring by barriers. Control module shall be locally programmable.
  1. System Memory: Nonvolatile. System shall reboot program and reset time automatically without errors after power outages up to 90 days' duration.
  2. Software: Lighting control software shall be capable of linking switch inputs to relay outputs, retrieving links, viewing relay output status, controlling relay outputs, simulating switch inputs, setting device addresses, and assigning switch input and relay output modes.
- D. Modular Relay Panel: Comply with UL 508 (CSA C22.2, No. 14) and UL 916 (CSA C22.2, No. 205); factory assembled with modular single-pole relays, power supplies, and accessory components required for specified performance.
  1. Cabinet: Steel with hinged, locking door.
    - a. Barriers separate low-voltage and line-voltage components.
    - b. Directory: Mounted on back of door. Identifies each relay as to load groups controlled and each programmed pilot device if any.
    - c. Control Power Supply: Transformer and full-wave rectifier with filtered dc output.
  2. Single-Pole Relays: Mechanically held unless otherwise indicated; split-coil, momentary-pulsed type.
    - a. Low-Voltage Leads: Plug connector to the connector strip in cabinet and pilot light power where indicated.

- b. Rated Capacity (Mounted in Relay Panel): 20 A, 125-V ac for tungsten filaments; 20 A, 277-V ac for ballasts.
  - c. Endurance: 50,000 cycles at rated capacity.
  - d. Mounting: Provision for easy removal and installation in relay cabinet.
- E. Push-Button Switches: Modular, momentary-contact, low-voltage type.
- 1. Match color specified in Division 16 Section "Wiring Devices."
  - 2. Integral green LED pilot light to indicate when circuit is on.
- F. Legend: Engraved or permanently silk-screened on wall plate where indicated. Use designations indicated on Drawings.
- G. Manufacturers: Subject to compliance with requirements, provide products by one of the following:
- 1. Z-Max from Colortran / Leviton Mfg. Company Inc.
  - 2. GRZ40 from Lighting Control & Design, Inc.
  - 3. Softswitch XP from Lutron Electronics Company, Inc.
  - 4. DMX Relay from Strand Lighting
  - 5. Smart Switch from ETC.

#### 2.15 ROAD SHOW DISCONNECT (COMPANY SWITCH):

- A. Manufacturers: Subject to compliance with requirements, provide products by one of the approved theatrical equipment manufacturers containing a circuit breaker by one of the following:
- a. Siemens/ITE
  - b. Cutler-Hammer Inc.
  - c. Furnas Electric Co.
  - d. General Electric Co.
  - e. Square D Company.
- B. Disconnect, General:
- a. Listing and Labeling: Provide switchgear assemblies that are listed and labeled. The terms "listed" and "labeled" shall be as defined in the National Electrical Code, Article 100.
  - b. General: Provide road show disconnect switches in types, sizes, duties, features ratings, and enclosures as indicated. Provide NEMA 1 enclosure. Provide protected pilot lamp connected to the output, indicating the status of the switch, safety cable supports, and interlocked front door for access to lugs bus bars and internal devices.
  - c. Automatic Circuit Breaker: Provide an adjustable trip multipole externally operable circuit breaker of proper rating to provide overcurrent and switch means.
  - d. Load Connections: Provide suitable output connectors for each pole, including ground and neutral. Provide 1 mating cable mounting connector for each output connector. Color code connections per NEC. Use Camlok connectors #14RTS 1040F.
  - e. Provide 3 phase 200 ampere 4 wire units for surface mounting.

#### 2.16 FINISHES

- A. Steel Parts: Manufacturers' standard black or dark color finishes for fixtures, accessories, and control components.
- B. Aluminum Housing and Wireway Parts: Manufacturers' standard black or dark color finishes.

- C. Aluminum Faceplates on Consoles and Control Stations: As approved by Architect/Engineer/Consultant.

### PART 3 - EXECUTION

#### 3.1 INSTALLATION

- A. Install equipment according to manufacturer's written instructions.
- B. Set permanently mounted items plumb and level and square with ceilings and walls.
- C. Mount and connect fixtures.
  - a. Arrange as indicated or so each fixture, each dimmer, each control console, each control receptacle and each control station can be operated and the system demonstrated in all operating modes. Contractor shall install every SP type lighting fixture as directed prior to delivery to owner.
- D. Mounting of Equipment: Conform to manufacturer's instructions and Division 16 Section "Supporting Devices."
- E. Mounting heights indicated are to bottom of unit for suspended items and to center of unit for wall-mounted ones.
- F. Wireway: Most new wiring to DM, R, and H panels shall be by steel wireway as shown. Homerun schedule on drawings shows only stage lighting loads. Installer shall figure worklight, houselight and all other loads to DM, H and R panels and calculate actual content of wireway. Provide overall 5% spare conductors in all wireways and conduits. Use these conductors for the benefit of the project if instructed by the engineer or consultant.

#### 3.2 ROUGH-IN

- A. Verify final locations for rough-ins with field measurements and with the requirements of the actual equipment to be connected.
- B. Refer to equipment specifications in Divisions 2 through 16 for rough-in requirements.

#### 3.3 CONTROL WIRING INSTALLATION

- A. Install wiring between control devices as specified in Division 16 Section "Wires and Cables" for hard wired connections. Install wiring in raceway except cable and plug connections.
- B. Wiring in Enclosures: Bundle, train, and support.

#### 3.3 FIELD QUALITY CONTROL

- A. Manufacturer's Field Services: Arrange and pay for the service of a factory-authorized service representative to test, adjust, and program the lighting control system.
- B. Reports: Prepare schedule of lighting outlets by number, indicating circuits, dimmers, connected fixtures, and control channel assignments. Prepare schedules of control settings for "House Control" preset scenes. Prepare written reports of tests and observations. Report defective materials and workmanship and unsatisfactory test results. Include records of repairs and adjustments made. Provide complete field reports by the commissioning service technician to the

engineer or consultant prior to final inspection.

- C. Test Labeling: Upon satisfactory completion of tests and observations, apply a label to tested components indicating test results, date, and responsible organization and person.
- D. Schedule visual and mechanical inspections and electrical tests with at least 7-days advanced notification.
- E. Visual and Mechanical Inspections: Include the following.
  - a. Inspect each fixture, outlet, module, and item of equipment for defects, finish failure, corrosion, and physical damage, NRTL labeling, and nameplate.
  - b. Exercise and perform operational tests on mechanical parts and operable devices according to manufacturer's instructions or routine functional operation.
  - c. Check tightness of electrical connections with torque wrench calibrated within the previous 6 months. Use manufacturer's recommended torque values.
  - d. Verify proper protective device settings and fuse types and ratings.
- F. Electrical Tests: Perform according to manufacturer's instructions. Exercise caution testing devices containing solid-state components.
  - a. Insulation resistance tests of conducting parts of control components and connecting supply feeder and control circuits. Minimum acceptable insulation resistance is 100 megohms or greater.
  - b. Continuity tests of all circuits. Certify this is completed to engineer or consultant.

### 3.4 CLEANING AND ADJUSTING

- A. Remove paint splatters and other spots, dirt, and debris. Repair scratches and mars of finish to match original finish. Clean fixtures, devices, and equipment internally and externally using methods and materials as recommended by manufacturers.
- B. Occupancy Adjustments: Within 1 year of Substantial Completion, conduct 3 on-site visits to assist in making program changes, and system and equipment adjustments.

### 3.5 DEMONSTRATION

- A. Demonstrate functions, features, and adjustments for each fixture with fixture energized and operating with the indicated lamp.
- B. Demonstrate the system to prove compliance with requirements.
- C. Direct Training: Arrange and pay for the services of a factory-authorized service representative to demonstrate lighting control system and train Owner's maintenance personnel.
  - a. Conduct a minimum of 8 hours of training in operation and maintenance as specified under "Instructions to Owner's Employees" in Division 1 Section "Project Closeout." Include training relating to system operation and maintenance procedures.
  - b. Schedule training with at least a 7-day advance notification.

### 3.6 COMMISSIONING

- A. Commissioning Orientation: Commissioning agent shall contact consultant prior to arrival at jobsite to be briefed on configuration requirements and project requirements.

- B. Operational Tests: Energize lighting controls systems, program controls, and check every controlled outlets for circuiting integrity. Verify proper operation of each control device and each control location. Program test scenes so every fixture is tested throughout its operating range with the installed lamp. Check programmed function at each house control, entry, and emergency light control station. Adjust components and revise installation to correct deficiencies. Provide Consultant with a copy of manufacturer's field service report, showing initial problems, resolutions and open items, after each service trip to the jobsite.
- B. Correct deficiencies and retest deficient items. Verify by the system tests that specified requirements are met.
- D. Provide all required instruction and maintenance manuals, training video tapes, spare parts, loose parts, and similar items. Deliver to the owner's representative, obtain a signed receipt, and forward a copy of the receipt to the Consultant.

END OF SECTION 265561